

DYNACODE II IP

Interface Description



Copyright by Carl Valentin GmbH / 7957315.0823

Information on the scope of delivery, appearance, performance, dimensions, and weight reflect our knowledge at the time of printing.

We reserve the rights to make modifications.

All rights, including those regarding the translation, are reserved.

No part of this document may be reproduced in any form (print, photocopy, or any other method) or edited, copied, or distributed electronically without written permission from Carl Valentin GmbH.

Due to the constant further development of our devices discrepancies between manual and device can occur.

Please check www.carl-valentin.de for the latest update.

Trademarks

All named brands or trademarks are registered brands or registered trademarks of their respective owners and may not be separately labelled. It must not be concluded from the missing labelling that it is not a registered brand or a registered trademark.

Carl Valentin direct print modules comply with the following EU directives:

CE Low-Voltage Directive (2014/35/EU)

Electromagnetic Compatibility Directive (2014/30/EU)



Carl Valentin GmbH

Postfach 3744

78026 Villingen-Schwenningen

Neckarstraße 78 – 86 u. 94

78056 Villingen-Schwenningen

Phone +49 7720 9712-0

Fax +49 7720 9712-9901

E-Mail info@carl-valentin.de

Internet www.carl-valentin.de

Table of Contents

1	Serial Data Transmission	5
1.1	Connector Assignment (9-pin DSUB Socket)	5
1.2	Connection Plan RS232	6
2	Parallel Data Transmission	7
2.1	Connection Plan	7
3	Text, Bar Code, Graphic	9
3.1	Definition of Rotation	9
3.2	Definition of Datum Point	9
4	Data Format	11
4.1	Explication	12
4.2	Definition of Field Attributes/Field Properties (optional)	13
4.3	Field Name	14
4.4	Field Selection by Free Definable Field Number	18
5	Mask Set	19
5.1	Text	19
5.2	One-Dimensional Bar Code	21
5.3	ITF Bar Code	22
5.4	PDF417	23
5.5	MAXICODE	24
5.6	DataMatrix	25
5.7	GS1 DataMatrix	26
5.8	CODABLOCK F	27
5.9	GS1 DataBar (RSS Code)	28
5.10	QR Code	29
5.11	Aztec Code	30
5.12	Rectangle	31
5.13	Line	31
5.14	Internal Graphic	32
6	Text Set	33
6.1	Examples	34
7	Graphic Set	35
7.1	General Graphic Format	35
7.2	Graphic in PCX Format	35
7.3	Example PCX File	36
8	Variables	37
8.1	Set Structure	37
8.2	Link Field	37
8.3	Counter	38
8.4	Extended Counter	39
8.5	Date and Time	40
8.6	Format Identifier (Date & Time)	41
8.7	Currency Variable	44
8.8	Shift Variable	45
8.9	User Guiding	46
8.10	User Guiding with Mask	47
8.11	Memory Card Data	48
8.12	GS1-128 Parser	48
8.13	EPC Calculation (Electronic Product Code)	49
8.14	Check Digit	50
8.15	Substring	51

9	Parameter Sets	53
9.1	Layout Parameters	53
9.2	Device Settings.....	57
9.3	Interface.....	62
9.4	Network	64
9.5	Sensors	68
9.6	Offset Values	68
9.7	Service Functions.....	69
9.8	Date & Time.....	72
9.9	Password.....	75
9.10	Compact Flash Card	77
9.11	Printing	81
9.12	Emulation.....	85
10	Parameter Sets for C Mode	87
10.1	Machine Parameters	87
10.2	Ribbon Save	89
10.3	I/O Parameters	91
11	Parameter Sets for I Mode	93
11.1	Machine Parameters	93
11.2	I/O Parameters	95
12	Configuration & Status	99
12.1	Autostatus.....	100
13	Monitored Printing.....	103
13.1	Short Introduction	103
13.2	Parameter Sets (Host – Printer)	103
13.3	Direct Enquiry	104
13.4	Answer Sets (Printer – Host).....	104
13.5	Sample Label.....	106
14	Font Examples	107
14.1	Bitmap Fonts (Not Proportional).....	107
14.2	Bitmap Fonts (Proportional)	107
14.3	Vector Fonts	107
15	Index	109

1 Serial Data Transmission



1.1 Connector Assignment (9-pin DSUB Socket)





Pin	Signal	Description
2	T x D	Transmitting data line
3	R x D	Receiving data line
5	GND	GND signal
7	CTS	HW handshake
8	RTS	HW handshake

1.2 Connection Plan RS232

Software Handshake



Hardware Handshake




2 Parallel Data Transmission

2.1 Connection Plan

Signal Pin no.	Signal name	Direction	Function
1	$\overline{\text{STROBE}}$	(Input)	The $\overline{\text{STROBE}}$ signal indicates that data can be received. The impulse width to the receiving line has to be 0,5 μs at least.
2	DATA 0	(Input)	The signals are data bits sent to the direct print module. A HIGH level corresponds to logical 1 and a LOW level to logical 0.
3	DATA 1	(Input)	
4	DATA 2	(Input)	
5	DATA 3	(Input)	
6	DATA 4	(Input)	
7	DATA 5	(Input)	
8	DATA 6	(Input)	
9	DATA 7	(Input)	
10	ACK/	(Output)	An impulse of approx. 12 μs confirms data input for a LOW level and signalizes the further listening watch of the direct print module.
11	BUSY	(Output)	A HIGH level indicates that the direct print module cannot receive any data. On the following conditions the signal HIGH is possible: 1) for data input (impulse for each sign) 2) during a printing process 3) in Offline status 4) for printing systems failures
12	PE	(Output)	A HIGH level indicates that paper is used up.
13	SELECT	(Output)	High Online
14	AUTOFEED	(Output)	Signal goes to LOW, in case 1) the paper is used up 2) the direct print module is Offline or 3) an error occurs.
15	FAULT/		
16	INIT/	(Input)	A LOW level initializes the direct print module
17	SELECTIN/	(Input)	A LOW level informs the direct print module to be addressed
18-25	GND		

3 Text, Bar Code, Graphic


3.1 Definition of Rotation



3.2 Definition of Datum Point

The so-called datum point is the relation point for indication of position. In the meantime the datum point is also the point at which the selected object is rotated.

To determine the datum point in the mask sets, the possible datum points are numbered from left top (1) to right bottom (9). The default datum point is left bottom (7). This datum point is also used even if no indication is found in the mask set.



4.1 Explication

x coordinate: Distance from right layout rim in mm
Measured from the right layout rim up to the lower left point of the corresponding line

y coordinate: Distance from upper layout rim in mm
Measured from the beginning of the layout down to the lower left point of the corresponding line

Bitmap fonts (not proportional)

01 = Font 01	0,8 x 1,1 mm	127 characters
02 = Font 02	1,2 x 1,7 mm	255 characters
03 = Font 03	1,8 x 2,6 mm	255 characters
04 = Font 04	4,0 x 5,6 mm	127 characters
05 = Font 05	1,8 x 3,2 mm (descender)	255 characters
06 = Font 06	1,5 x 2,9 mm	127 characters
07 = Font 07	1,2 x 2,2 mm (descender)	255 characters

Bitmap fonts (proportional)

21 = Font 21	(1,0; 13)	255 characters
22 = Font 22	(1,8; 21)	255 characters
23 = Font 23	(2,6; 31)	255 characters
24 = Font 24	(5,6; 67)	255 characters
28 = Font 28	(4,0; 48)	255 characters
29 = Font 29	(0,8; 9)	255 characters



NOTICE!

In order to reach best print results it is recommended always to choose the biggest possible font.

Vector fonts (proportional)

When in mode 'proportional text', the height and width of text have to be entered in mm.
These values refer to the capital 'M', i.e. the values of other characters are changing in proportion.

Vector fonts (autoscale)

When in autoscale mode, height and width of text has to be entered in mm.
The height of the text refers to all capital letters. When using small characters and descenders the height is changing in proportion. When entering the width, the complete file has to be considered. The text will be adjusted automatically, which means that the width of the characters is changing.

4.2 Definition of Field Attributes/Field Properties (optional)

Explanation

Additionally to mask set 'AM[] ...' the possibility was created to define further field properties. In order to achieve a high flexibility, the field properties received own names/identifications. Therefore the sequence as well as the number of field properties is free. If necessary, the mask set 'AC[]' is transferred additionally to mask set 'AM[]' to the direct print module.

Structure mask set

(SOH)AC[]at1=*value*;at2= *value*;...(ETB)

Attribute (at):	Description
BT BW QZ	ITF 14 (see page 22) bearer bar type bearer bar width quiet zone in 1/100 mm
NAME	Field name (see page 14) definition of field name
FN	Field number (see page 18) Free definable field number


This table is constantly extended. The current version is available on demand.

4.3 Field Name

Application (customized)

When direct print modules are connected to a computer system or machine controls, there is often the requirement that variable data is to be inserted into an existing layout. This data contents come from the superordinate computer system (database) or a machine control (e.g. PLC, scale, ERP system, etc.). Basically, it was always possible to integrate variable data into a 'loaded' layout (mask). The access to certain fields has been effected via the field index, i.e. a consecutive number. This field index is generated by Labelstar Office and can also change with layout changes, whereby the data allocation to the computer system/control is no longer correct.

Example



Print data

```

...
// TEXT (1/100 mm)
(SOH)AM[1]2405;803;0;1;2;4;1;1;0(ETB)
(SOH)BM[1]Feld 1(ETB)
// TEXT (1/100 mm)
(SOH)AM[2]421;856;0;1;2;4;1;1;0(ETB)
(SOH)BM[2]Feld 2(ETB)
// LINES: 2
...

```

The print data contains the definitions for the two text fields. The field index is always in '[']' of the mask or text setting.

If the text field 'Feld 1' is deleted on the layout and then recreated, it gets a new index. In this case '2'. The text field 'Feld 2' gets the index '1'. As a result, an assignment via the field index is used only to a limited extent, without manual post-processing of the layout data.

Explanation

As an alternative to the field index, the assignment can also be made via the field name. A change in the field index has no longer any influence, and a changed layout is still filled in the right places with variable data of the computer system/control system.

Labelstar Office: The print data is supplemented by the following line:

(SOH)AC[1]NAME="Field name"(ETB)


The field content defined via the text block can be changed by the computer system/control with the following command:

(SOH)BV[Field name]Feld 2(ETB)

This results in the following standard procedure for the connection to a high-level control and/or computer system.


Layout design with Labelstar Office

The field names are automatically transferred by Labelstar Office.





The desired field name (Field1) is entered in the properties of the text field.

For text fields, a printer-internal font must be used. The device-internal fonts are marked by a printer symbol in the list.



Export to a print file and save the layout in the external controller

When the layout design is finished, the layout is exported to a print file. For this, Labelstar Office uses the function **File – Export – Create Print Template**.




The option **Create separate data file** must be selected, otherwise the line (SOH)**FBC---r-----**(ETB) is included in the print file, which would immediately release a print procedure.

By starting a print procedure, this print file (layout definition / mask definition) is transferred from the controller/computer system to the direct print module first.

Save the layout on the memory card of the direct print module

As an alternative to 'Export to a print file' the layout is saved on the memory card of the direct print module. For this, the memory card tool from Labelstar Office can be used.



The layout must be called by the controller/computer system **before** filling the variable fields.

The following parameter set is used:

(SOH)**FMA---rfilename**(ETB)

The path name is determined when saving and possibly contains a path.

Example: "A:\Standard\eti1".

Filling the variable fields by the controller/computer system

The higher-level control can select the variable fields by the field names and set the contents. Subsequently, the print job is restarted.

Example	(SOH)FMB---rfilename(ETB)	Loading the layout from mc
	(SOH)BV[ArtBez]screws(ETB)	Filling the field "ArtBez" with "screws"
	(SOH)BV[ArtNr]123456789(ETB)	Filling the field "ArtNr" with "123456789"
	(SOH)FBC---r------(ETB)	Start printing

4.4 Field Selection by Free Definable Field Number

With the following described attribute, it is possible to assign a free definable field number to a field. This field number does not have to be clear, i.e. several fields can have the same field number. In this way the same field contents can be assigned to different fields.

The following attribute identification is defined:

Attribute: **FN**

Description: free definable field number

After the field number was assigned with AC mask statement,

(SOH) AC [n] FN=nr (ETB)

n = field index

nr = free definable field number

it is possible to access to the field and/or the fields with the new BF text statement:

(SOH) BF [nr] text (ETB)

nr = field number

text = field contents

Example	<code>// Assignment of field number field 1 and field 2</code>
	<code>(SOH)AM[1]1000;2500;0;4;2;7;400;400;0(ETB)</code>
	<code>(SOH) AC [1] FN=100 (ETB)</code>
	<code>(SOH)AM[2]2000;2500;0;30;2;4000;9;3;0;1(ETB)</code>
	<code>(SOH) AC [2] FN=100 (ETB)</code>
	<code>// Access to field 1 and field 2 by field number</code>
	<code>(SOH) BF [100]1234567890(ETB)</code>

dy	extension in direction Y bitmap fonts factor 0...9 bektor fonts character size in 1/100 mm vector fonts autoscale field height
dx	extension in direction X bitmap fonts factor 0-9 bektor fonts character size in 1/100 mm vector fonts autoscale field width
lp	distance between single characters in 1/100 mm
dp	datum point 1 = left top 2 = centre top 3 = right top 4 = left centre 5 = centre centre 6 = right centre 7 = left bottom (default) 8 = centre bottom 9 = right bottom

5.4 PDF417

AM[n];x;p:a;d;s;rw;rh;ec;z;dp;c;r	
A	identification for mask set
M	identification for protocol version
n	Field number
y	Y position in 1/100 mm
x	X position in 1/100 mm
p	identification for phantom field 0 = print 1 = no print
a	identification for field type 50 = PDF417
d	rotation 0 = 0° 1 = 90° 2 = 180° 3 = 270°
s	symbol size
rw	relation width
rh	relation height
ec	error correction level 0 - ECC Level = 0 1 - ECC Level = 2 2 - ECC Level = 6 3 - ECC Level = 14 4 - ECC Level = 30 5 - ECC Level = 62 6 - ECC Level = 126 7 - ECC Level = 254 8 - ECC Level = 510
z	style 0 = standard 1 = truncated 2 = naked 3 = bare
dp	datum point 1 = left top 2 = centre top 3 = right top 4 = left centre 5 = centre centre 6 = right centre 7 = left bottom (default) 8 = centre bottom 9 = right bottom
c	number of columns 0 = automatic, 1-30
r	number of rows 0 = automatic, 3-90

5.5 MAXICODE

AM[n;y;x;p;a;d;0;sn;ns;m;0;dp	
A	identification for mask set
M	identification for protocol version
n	field number
y	Y position in 1/100 mm
x	X position in 1/100 mm
p	identification for phantom field 0 = print 1 = no print
a	identification for field type 51 = MAXICODE
d	rotation 0 = 0° 1 = 90° 2 = 180° 3 = 270°
0	dummy
sn	symbol number
ns	quantity of symbols
m	mode 2 = Structured Message (US Carrier) 3 = Structured Message (International Carrier) 4 = Default message
0	dummy
dp	datum point 1 = left top 2 = centre top 3 = right top 4 = left centre 5 = centre centre 6 = right centre 7 = left bottom (default) 8 = centre bottom 9 = right bottom

5.6 DataMatrix

AM[n];y;x;p;a;d;s;aw;ah;ec;f;dp																															
A	identification for mask set																														
M	identification for protocol version																														
n	field number																														
y	Y position in 1/100 mm																														
x	X position in 1/100 mm																														
p	identification for phantom field 0 = print 1 = no print																														
a	identification for field type 52 = DataMatrix																														
d	rotation 0 = 0° 1 = 90° 2 = 180° 3 = 270°																														
s	symbol size in 1/100 mm																														
aw	relation width																														
ah	relation height																														
ec	Error Correction <table style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 33%;">0 - ECC Type = 0</td> <td style="width: 33%;">ECC Level = 0</td> <td style="width: 33%;">Overhead = 0 %</td> </tr> <tr> <td>1 - ECC Type = 2*</td> <td>ECC Level = 40</td> <td>Overhead = 33 %</td> </tr> <tr> <td>2 - ECC Type = 3</td> <td>ECC Level = 50</td> <td>Overhead = 25 %</td> </tr> <tr> <td>3 - ECC Type = 6</td> <td>ECC Level = 80</td> <td>Overhead = 33 %</td> </tr> <tr> <td>4 - ECC Type = 8</td> <td>ECC Level = 100</td> <td>Overhead = 50 %</td> </tr> <tr> <td>5 - ECC Type = 9*</td> <td>ECC Level = 110</td> <td>Overhead = 75 %</td> </tr> <tr> <td>6 - ECC Type = 10*</td> <td>ECC Level = 120</td> <td>Overhead = 50 %</td> </tr> <tr> <td>7 - ECC Type = 11*</td> <td>ECC Level = 130</td> <td>Overhead = 67 %</td> </tr> <tr> <td>8 - ECC Type = 12</td> <td>ECC Level = 140</td> <td>Overhead = 75 %</td> </tr> <tr> <td>9 - ECC Type = 26</td> <td>ECC Level = 200</td> <td>Overhead = 0 %</td> </tr> </table>	0 - ECC Type = 0	ECC Level = 0	Overhead = 0 %	1 - ECC Type = 2*	ECC Level = 40	Overhead = 33 %	2 - ECC Type = 3	ECC Level = 50	Overhead = 25 %	3 - ECC Type = 6	ECC Level = 80	Overhead = 33 %	4 - ECC Type = 8	ECC Level = 100	Overhead = 50 %	5 - ECC Type = 9*	ECC Level = 110	Overhead = 75 %	6 - ECC Type = 10*	ECC Level = 120	Overhead = 50 %	7 - ECC Type = 11*	ECC Level = 130	Overhead = 67 %	8 - ECC Type = 12	ECC Level = 140	Overhead = 75 %	9 - ECC Type = 26	ECC Level = 200	Overhead = 0 %
0 - ECC Type = 0	ECC Level = 0	Overhead = 0 %																													
1 - ECC Type = 2*	ECC Level = 40	Overhead = 33 %																													
2 - ECC Type = 3	ECC Level = 50	Overhead = 25 %																													
3 - ECC Type = 6	ECC Level = 80	Overhead = 33 %																													
4 - ECC Type = 8	ECC Level = 100	Overhead = 50 %																													
5 - ECC Type = 9*	ECC Level = 110	Overhead = 75 %																													
6 - ECC Type = 10*	ECC Level = 120	Overhead = 50 %																													
7 - ECC Type = 11*	ECC Level = 130	Overhead = 67 %																													
8 - ECC Type = 12	ECC Level = 140	Overhead = 75 %																													
9 - ECC Type = 26	ECC Level = 200	Overhead = 0 %																													
f	format ID of data 0 - Format ID = 11 (numeric, 2000 characters)* 1 - Format ID = 1 (numeric, 500 characters) 2 - Format ID = 2 (alphabetical, 500 characters) 3 - Format ID = 3 (alphabetical + pointers, 500 characters) 4 - Format ID = 4 (alphanumeric, 500 characters) 5 - Format ID = 5 (7 Bit, 500 characters) 6 - Format ID = 6 (8 Bit, 500 characters) 7 - Format ID = 7 (pre-programmed, 500 characters)* 8 - Format ID = 12 (alphabetical, 2000 characters) 9 - Format ID = 14 (alphanumeric, 2000 characters)																														
dp	datum point 1 = left top 2 = centre top 3 = right top 4 = left centre 5 = centre centre 6 = right centre 7 = left bottom (default) 8 = centre bottom 9 = right bottom																														

* not supported

5.7 GS1 DataMatrix

AM[n]y;x;p;a;d;s;aw;ah;ec;f;dp																															
A	identification for mask set																														
M	identification for protocol version																														
n	field number																														
y	Y position in 1/100 mm																														
x	X position in 1/100 mm																														
p	identification for phantom field 0 = print 1 = no print																														
a	identification for field type 59 = GS1 DataMatrix																														
d	rotation 0 = 0° 1 = 90° 2 = 180° 3 = 270°																														
s	symbol size in 1/100 mm																														
aw	relation width																														
ah	relation height																														
ec	Error Correction <table style="width: 100%; border-collapse: collapse;"> <tr> <td style="width: 33%;">0 - ECC Type = 0</td> <td style="width: 33%;">ECC Level = 0</td> <td style="width: 33%;">Overhead = 0 %</td> </tr> <tr> <td>1 - ECC Type = 2*</td> <td>ECC Level = 40</td> <td>Overhead = 33 %</td> </tr> <tr> <td>2 - ECC Type = 3</td> <td>ECC Level = 50</td> <td>Overhead = 25 %</td> </tr> <tr> <td>3 - ECC Type = 6</td> <td>ECC Level = 80</td> <td>Overhead = 33 %</td> </tr> <tr> <td>4 - ECC Type = 8</td> <td>ECC Level = 100</td> <td>Overhead = 50 %</td> </tr> <tr> <td>5 - ECC Type = 9*</td> <td>ECC Level = 110</td> <td>Overhead = 75 %</td> </tr> <tr> <td>6 - ECC Type = 10*</td> <td>ECC Level = 120</td> <td>Overhead = 50 %</td> </tr> <tr> <td>7 - ECC Type = 11*</td> <td>ECC Level = 130</td> <td>Overhead = 67 %</td> </tr> <tr> <td>8 - ECC Type = 12</td> <td>ECC Level = 140</td> <td>Overhead = 75 %</td> </tr> <tr> <td>9 - ECC Type = 26</td> <td>ECC Level = 200</td> <td>Overhead = 0 %</td> </tr> </table>	0 - ECC Type = 0	ECC Level = 0	Overhead = 0 %	1 - ECC Type = 2*	ECC Level = 40	Overhead = 33 %	2 - ECC Type = 3	ECC Level = 50	Overhead = 25 %	3 - ECC Type = 6	ECC Level = 80	Overhead = 33 %	4 - ECC Type = 8	ECC Level = 100	Overhead = 50 %	5 - ECC Type = 9*	ECC Level = 110	Overhead = 75 %	6 - ECC Type = 10*	ECC Level = 120	Overhead = 50 %	7 - ECC Type = 11*	ECC Level = 130	Overhead = 67 %	8 - ECC Type = 12	ECC Level = 140	Overhead = 75 %	9 - ECC Type = 26	ECC Level = 200	Overhead = 0 %
0 - ECC Type = 0	ECC Level = 0	Overhead = 0 %																													
1 - ECC Type = 2*	ECC Level = 40	Overhead = 33 %																													
2 - ECC Type = 3	ECC Level = 50	Overhead = 25 %																													
3 - ECC Type = 6	ECC Level = 80	Overhead = 33 %																													
4 - ECC Type = 8	ECC Level = 100	Overhead = 50 %																													
5 - ECC Type = 9*	ECC Level = 110	Overhead = 75 %																													
6 - ECC Type = 10*	ECC Level = 120	Overhead = 50 %																													
7 - ECC Type = 11*	ECC Level = 130	Overhead = 67 %																													
8 - ECC Type = 12	ECC Level = 140	Overhead = 75 %																													
9 - ECC Type = 26	ECC Level = 200	Overhead = 0 %																													
f	format ID of data 0 - Format ID = 11 (numeric, 2000 characters)* 1 - Format ID = 1 (numeric, 500 characters) 2 - Format ID = 2 (alphabetical, 500 characters) 3 - Format ID = 3 (alphabetical + pointers, 500 characters) 4 - Format ID = 4 (alphanumeric, 500 characters) 5 - Format ID = 5 (7 Bit, 500 characters) 6 - Format ID = 6 (8 Bit, 500 characters) 7 - Format ID = 7 (pre-programmed, 500 characters)* 8 - Format ID = 12 (alphabetical, 2000 characters) 9 - Format ID = 14 (alphanumeric, 2000 characters)																														
dp	datum point 1 = left top 2 = centre top 3 = right top 4 = left centre 5 = centre centre 6 = right centre 7 = left bottom (default) 8 = centre bottom 9 = right bottom																														

* not supported

5.8 CODABLOCK F

AM[n]y;x;p;a;d;h;nc;nl;m;s;dp	
A	identification for mask set
M	identification for protocol version
n	field number
y	Y position in 1/100 mm
x	X position in 1/100 mm
p	identification for phantom field 0 = printout 1 = np printout
a	identification for field type 53 = CODABLOCK F
d	rotation 0 = 0° 1 = 90° 2 = 180° 3 = 270°
h	line height in symbol
nc	quantity of characters/line
nl	quantity of lines
m	mode
s	module size
dp	datum point 1 = left top 2 = centre top 3 = right top 4 = left centre 5 = centre centre 6 = right centre 7 = left bottom (default) 8 = centre bottom 9 = right bottom

5.9 GS1 DataBar (RSS Code)

AM[n]y;x;p;a;d;s;m;k;t;0;dp	
A	identification for mask set
M	identification for protocol version
n	field number
y	Y position in 1/100 mm
x	X position in 1/100 mm
p	identification for phantom field 0 = print 1 = no print
a	identification for field type 54 = GS1 DataBar (RSS)
d	rotation 0 = 0° 1 = 90° 2 = 180° 3 = 270°
s	number of segments per line [2...22]
m	module width [1 ...12]
k	separator height [1,2]
t	symbol type 1 = GS1 DataBar Omnidirectional (RSS-14) 2 = GS1 DataBar Truncated (RSS-14 Truncated) 3 = GS1 DataBar Stacked (RSS-14 Stacked) 4 = GS1 DataBar Stacked Omnidirectional (RSS-14 Stacked Omnidirectional) 5 = GS1 DataBar Limited (RSS Limited) 6 = GS1 DataBar Expanded (RSS Expanded)
0	not used
dp	datum point 1 = left top 2 = centre top 3 = right top 4 = left centre 5 = centre centre 6 = right centre 7 = left bottom (default) 8 = centre bottom 9 = right bottom

5.10 QR Code

AM[n];y;x;p;a;d;mo;cs;ms;cw;ec;dp	
A	identification for mask set
M	identification for protocol version
n	field number
y	Y position in 1/100 mm
x	X position in 1/100 mm
p	identification for phantom field 0 = print 1 = no print
a	identification for field type 57 = QR Code
d	rotation 0 = 0° 1 = 90° 2 = 180° 3 = 270°
mo	code model 1 = Code Model 1 2 = Code Model 2
cs	character set N = numeric A = alphanumeric B = 8-bit byte K = kanji
ms	masking -1 = auto 0-7 = mask x 8 = no masking
cw	line width in 1/100 mm per module possible values: 0-800
ec	error correction (restoring capacity) L = 7 % M = 15 % Q = 25 % H = 30 %
dp	datum point 1 = left top 2 = centre top 3 = right top 4 = left centre 5 = centre centre 6 = right centre 7 = left bottom (default) 8 = centre bottom 9 = right bottom

5.11 Aztec Code

AM[n]y;x;p;a;d;h;f;ec;m;0;dp																																							
A	identification for mask set																																						
M	identification for protocol version																																						
n	field number																																						
y	Y position in 1/100 mm																																						
x	X position in 1/100 mm																																						
p	identification for phantom field 0 = print 1 = no print																																						
a	identification for field type 61 = Aztec Code																																						
d	rotation 0 = 0° 1 = 90° 2 = 180° 3 = 270°																																						
h	symbol size in 1/100 mm (max 1 cm)																																						
f	format <table style="width: 100%; border: none;"> <tr> <td>0 = Auto</td> <td>19 = C79xC79</td> </tr> <tr> <td>1 = C15xC15 Compact</td> <td>20 = C83xC83</td> </tr> <tr> <td>2 = C19xC19 Compact</td> <td>21 = C87xC87</td> </tr> <tr> <td>3 = C23xC23 Compact</td> <td>22 = C91xC91</td> </tr> <tr> <td>4 = C27xC27 Compact</td> <td>23 = C95xC95</td> </tr> <tr> <td>5 = C19xC19</td> <td>24 = C101xC101</td> </tr> <tr> <td>6 = C23xC23</td> <td>25 = C105xC105</td> </tr> <tr> <td>7 = C27xC27</td> <td>26 = C109xC109</td> </tr> <tr> <td>8 = C31xC31</td> <td>27 = C113xC113</td> </tr> <tr> <td>9 = C37xC37</td> <td>28 = C117xC117</td> </tr> <tr> <td>10 = C41xC41</td> <td>29 = C121xC121</td> </tr> <tr> <td>11 = C45xC45</td> <td>30 = C125xC125</td> </tr> <tr> <td>12 = C49xC49</td> <td>31 = C131xC131</td> </tr> <tr> <td>13 = C53xC53</td> <td>32 = C135xC135</td> </tr> <tr> <td>14 = C57xC57</td> <td>33 = C139xC139</td> </tr> <tr> <td>15 = C61xC61</td> <td>34 = C143xC143</td> </tr> <tr> <td>16 = C67xC67</td> <td>35 = C147xC147</td> </tr> <tr> <td>17 = C71xC71</td> <td>36 = C151xC151</td> </tr> <tr> <td>18 = C75xC75</td> <td></td> </tr> </table>	0 = Auto	19 = C79xC79	1 = C15xC15 Compact	20 = C83xC83	2 = C19xC19 Compact	21 = C87xC87	3 = C23xC23 Compact	22 = C91xC91	4 = C27xC27 Compact	23 = C95xC95	5 = C19xC19	24 = C101xC101	6 = C23xC23	25 = C105xC105	7 = C27xC27	26 = C109xC109	8 = C31xC31	27 = C113xC113	9 = C37xC37	28 = C117xC117	10 = C41xC41	29 = C121xC121	11 = C45xC45	30 = C125xC125	12 = C49xC49	31 = C131xC131	13 = C53xC53	32 = C135xC135	14 = C57xC57	33 = C139xC139	15 = C61xC61	34 = C143xC143	16 = C67xC67	35 = C147xC147	17 = C71xC71	36 = C151xC151	18 = C75xC75	
0 = Auto	19 = C79xC79																																						
1 = C15xC15 Compact	20 = C83xC83																																						
2 = C19xC19 Compact	21 = C87xC87																																						
3 = C23xC23 Compact	22 = C91xC91																																						
4 = C27xC27 Compact	23 = C95xC95																																						
5 = C19xC19	24 = C101xC101																																						
6 = C23xC23	25 = C105xC105																																						
7 = C27xC27	26 = C109xC109																																						
8 = C31xC31	27 = C113xC113																																						
9 = C37xC37	28 = C117xC117																																						
10 = C41xC41	29 = C121xC121																																						
11 = C45xC45	30 = C125xC125																																						
12 = C49xC49	31 = C131xC131																																						
13 = C53xC53	32 = C135xC135																																						
14 = C57xC57	33 = C139xC139																																						
15 = C61xC61	34 = C143xC143																																						
16 = C67xC67	35 = C147xC147																																						
17 = C71xC71	36 = C151xC151																																						
18 = C75xC75																																							
ec	error correction (only if format = 0) 1 = 10 % 2 = 23 % 3 = 36 % 4 = 50 %																																						
m	mode 0 = data 1 = runes (figures 0-255) 2 = Unicode (8 Bit ASCII) 3 = GS1 (not yet available)																																						
0	dummy																																						
dp	datum point 1 = left top 2 = centre top 3 = right top 4 = left centre 5 = centre centre 6 = right centre 7 = left bottom (default) 8 = centre bottom 9 = right bottom																																						

5.12 Rectangle

AM[n]y;x;p;a;h;b;s;m;dp	
A	identification for mask set
M	identification for protocol version
n	field number
y	Y position in 1/100 mm
x	X position in 1/100 mm
p	identification for phantom field 0 = print 1 = no print
a	identification for field type 10 = rectangle
h	rectangle height in 1/100 mm
b	rectangle height in 1/100 mm
s	line width in 1/100 mm
m	line type; 1 digit
dp	datum point 1 = left top 2 = centre top 3 = right top 4 = left centre 5 = centre centre 6 = right centre 7 = left bottom (default) 8 = centre bottom 9 = right bottom

5.13 Line

AM[n]y;x;p;a;d;l;s;m;dp	
A	identification for mask set
M	identification for protocol version
n	field number
y	Y position in 1/100 mm
x	X position in 1/100 mm
p	identification for phantom field 0 = printout 1 = no printout
a	identification for field type 11 = line
d	rotation 0 = horizontal 1 = vertical
l	length in 1/100 mm
s	line width in 1/100 mm
m	line type; 1 digit
dp	datum point 1 = left top 2 = centre top 3 = right top 4 = left centre 5 = centre centre 6 = right centre 7 = left bottom (default) 8 = centre bottom 9 = right bottom

5.14 Internal Graphic

AM[n]y;x;p;a;d;dy;dx;dp	
A	identification for mask set
M	identification for protocol version
n	field number
y	Y position in 1/100 mm
x	X position in 1/100 mm
P	identification for phantom field 0 = print 1 = no print
a	identification for field type 3 = internal graphic
d	rotation 0 = 0° 1 = 90° 2 = 180° 3 = 270°
dy	rotation in direction Y
dx	rotation in direction X
dp	datum point 1 = left top 2 = centre top 3 = right top 4 = left centre 5 = centre centre 6 = right centre 7 = left bottom (default) 8 = centre bottom 9 = right bottom

6 Text Set

BM[n]text	
B	identification for text set
M	identification for extended protocol
n	field number
text	data contents, text

BV[n]text	
B	identification for text set
V	identification for selection by field name
n	field name
text	data contents, text

BF[n]text	
B	identification for text set
F	identification for selection by free definable field number
n	field number
text	data contents, text

6.1 Examples

Mask set

Mask statement	[SOH]AM[1]2000;4000;0;1;0;2;1;1;0[ETB]
field number	
y position 20 mm	
x position 40 mm	
no phantom field	
bitmap font	
position 0	
font 2	
extension in y direction 1	
extension in x direction 1	
no blank pixel	

Texts set

Text statement	[SOH]BM[1]this is a test [ETB]
field number 1	
text "this is a test"	

Text set with variable definition:

[SOH]BM[125]=CN(0,0,3,1,1)000[ETB]

Example layout

ASCII data	Identification
⊗AM[1]3600;4600;0;33;0;1500;0;4;1;1⊕ ^{C_R} ⊕ ^{L_F}	mask set for bar code
⊗BM[1]4444444444444⊕ ^{C_R} ⊕ ^{L_F}	appropriate text set
⊗AM[2]600;4700;0;4;0;1;300;200;24⊕ ^{C_R} ⊕ ^{L_F}	five mask sets vector font / proportional font
⊗AM[3]600;3100;0;4;0;1;400;300;24⊕ ^{C_R} ⊕ ^{L_F}	
⊗AM[4]1100;4700;0;4;0;1;400;300;24⊕ ^{C_R} ⊕ ^{L_F}	
⊗AM[5]1800;4700;0;4;0;1;300;200;24⊕ ^{C_R} ⊕ ^{L_F}	
⊗AM[6]1900;3700;0;4;0;1;600;400;24⊕ ^{C_R} ⊕ ^{L_F}	
⊗BM[2]Art.Nr. ⊕ ^{C_R} ⊕ ^{L_F}	five appropriate text sets
⊗BM[3]44444⊕ ^{C_R} ⊕ ^{L_F}	
⊗BM[4]Artikelbezeichnung⊕ ^{C_R} ⊕ ^{L_F}	
⊗BM[5]EUR⊕ ^{C_R} ⊕ ^{L_F}	
⊗BM[6]99,-- ⊕ ^{C_R} ⊕ ^{L_F}	
⊗FBA000r06000000⊕	number of lines
⊗FBBA00r00001000⊕	number of items
⊗FBC000r00000000⊕	start

: graphic data in PCX format
 ⊗: SOH (1_{hex} bzw 5E_{hex})
 ⊕: ETB (17_{hex} bzw. 5F_{hex})
^{C_R}: CarriageReturn (0D_{hex})
^{L_F}: LineFeed (0A_{hex})

- It is recommended to observe that directly after the final sign (ETB) no separator res. fill character such as $C_R L_F$ is indicated.
- The direct print module supports the following PCX versions: 5, 3, 2 and 0.
- It is necessary that the corresponding PCX-file is available as monochrome (black/white).
- The graphic has to be available in the original size as the direct print module is not able to change the size by itself.

**NOTICE!**

Before print start, indicated by parameter set 'FBC', the definition of field number, lines and pieces has to be effected via the parameter sets (FBA res. FBB).

7.3 Example PCX File

-*** PCX_GRAPHIC-INFO ***-

⊗AX0010015300100941⊕#####	
⊗AM[1]3600;4600;0;33;0;1500;0;4;1;1⊕ $C_R L_F$	mask set for bar code
⊗BM[1]444444444444⊕ $C_R L_F$	appropriate text set
⊗AM[2]600;4700;0;4;0;1;300;200;24⊕ $C_R L_F$ ⊗AM[3]600;3100;0;4;0;1;400;300;24⊕ $C_R L_F$ ⊗AM[4]1100;4700;0;4;0;1;400;300;24⊕ $C_R L_F$ ⊗AM[5]1800;4700;0;4;0;1;300;200;24⊕ $C_R L_F$ ⊗AM[6]1900;3700;0;4;0;1;600;400;24⊕ $C_R L_F$	five mask set vector font / proportional font
⊗BM[2]Art.Nr. ⊕ $C_R L_F$ ⊗BM[3]44444⊕ $C_R L_F$ ⊗BM[4]Artikelbezeichnung⊕ $C_R L_F$ ⊗BM[5]EUR⊕ $C_R L_F$ ⊗BM[6]99,-- ⊕ $C_R L_F$	five appropriate text sets
⊗FBA00r06000000⊕	set number of lines (FBA...)
⊗FBBA00r00001000⊕	set quantity (FBBA...)
⊗FBC000r00000000⊕	start print order (FBC...)

: Grafikdaten im PCX Format
⊗: SOH (1_{hex} bzw 5E_{hex})
⊕: ETB (17_{hex} bzw. 5F_{hex})
 C_R : CarriageReturn (0D_{hex})
 L_F : LineFeed (0A_{hex})

8 Variables

8.1 Set Structure

SOH	BM	[n]	=	v	v	(p1	p2	p...	pn)	t1	t2	t...	t70	ETB
-----	----	-----	---	---	---	---	----	----	------	----	---	----	----	------	-----	-----

= start of function
 vv variable type
 SC link field
 CN counter
 CC extended counter
 CL date/time
 CU currency variable
 SH shift variable
 MD memory card data
 (start of variable parameter block
 p1...pn variable parameter
) end of variable parameter block



NOTICE!

In case you want to print a text which corresponds exactly to the variable definition then you have to place '!' before.

SOH	BM	[n]	!	=	v	v	(p1	p2	p...	pn)	t1	t2	t...	t70	ETB
-----	----	-----	---	---	---	---	---	----	----	------	----	---	----	----	------	-----	-----

8.2 Link Field

SOH	BM	[n]	=	S	C	(p1	;	p2	;	p...	;	pn)	t1	t2	t...	t70	ETB
-----	----	-----	---	---	---	---	----	---	----	---	------	---	----	---	----	----	------	-----	-----

= SC identification of link field
 p1...pn identification of link elements (field number or constant text)
 field number is entered without leading '0'
 constant text is included in " but these marks are not printed



NOTICE!

Reference fields can be constant text or variables but no link fields.

Example

=SC(1;2;3) --> Printout: Field1Field2Field3

=SC(1;"constant";2) --> Printout: Field1constantField2

8.3 Counter

SOH	BM	[n]	=	C	N	(t	;	m	;	c	;	+/-	s	;	i	;	h	;	r)	t1	t2	t...	t70	ETB
-----	----	-----	---	---	---	---	---	---	---	---	---	---	-----	---	---	---	---	---	---	---	---	----	----	------	-----	-----

= CN	identification counter
t	type of counter
0	numerical
1	letters only
2...36	radix, base of the counter
m	function mode
0	standard
1	return to start value
2	enter the start value at the beginning of printing (default = existing start value)
3	enter the start value at the beginning of printing (default = last final number)
4	reset start value at cycle end (only for DPM IIIi)
5	reset start value by I/O signal
6	time-controlled resetting
7	time-controlled resetting with input of initial value (default = last final value)
c	digit where the numbering starts counting
+/-	direction
+	adding
-	subtracting
s	step width
i	update interval (number of layouts with identical number)
h	time by which the counter is reset (function mode 6 and 7) in format 'HH:MM' e.g. 00:00 = reset counter at 0:00 (optional, only for function mode 6 and 7)
r	reset value (optional, only for function mode 6 and 7; default = text and/or initial value)
	Limitation: The time-controlled resetting of counter variable is only effected in case of an active print order. If a print order is cancelled before the specified time and afterwards again restarted then no resetting of counter value is effected.
t1, t2, ...	text res. start value of counter

Example:

Input: =CN(10;7;4;+1;1;06:00;0001)1234

The enquiry for the initial value is effected at print start and at 6:00 the counter variable is reset to value 0001.

8.4 Extended Counter

SOH	BM	[n]	=	C	C	(+/-	s	;	i	;	m	;	z	;	n	;	x)	t	ETB
-----	----	-----	---	---	---	---	-----	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

= CC identification of numeric counter

+/- direction
 + counter adding
 - counter subtracting

s step width

i update interval
 (number of layouts with identical number)

m function mode
 0 standard
 1 return to start value
 2 enter the start value at the beginning of printing
 (default = existing start value)
 3 enter the start value at the beginning of printing
 (default = last final number)
 4 reset start value at cycle end
 (only for DPM IIIi)
 5 set min. / max. value
 6 set start value
 7 print end

z leading zeros
 0 no leading zeros
 1 printout with leading zeros

n minimum value (max. -999999999)

x maximum value (max. 999999999)

t start value
 (the number of digits determines the format for the printout with leading zeros
 (max. 999999999)

Example:

Input: =CC(+1;2;5;0;1,999)0050

Printout: 50, 51, ... 999, 1, 2, ...

8.5 Date and Time

```
SOHBM[n]=CL(m;d;i;n;c;mo;pd;pm;md;mm;rw;ws)t1t...t70ETB
```

= CL identification date/time

m month offset to the actual date

d day offset to the actual date

i update interval

(0 = at the beginning of a print order, 1 = each layout)

Optional parameters

n minute offset of the actual time
(negative entry/value possible)

c correction month overflow

(0 = change to the next month, 1 = remain in current month)

Optional parameters for BBE date

mo input mode

0: standard; display current date of real time clock

1: display calculated date, modification possible

2: display calculated date, no modification possible

pd max. positive correction days

pm max. positive correction months

md max. negative correction days

mm max. negative correction months

Optional parameters for rounded date

rw rounded weekday: 1 = Sunday ... 7 = Saturday; 0 = no rounding

ws start of week, format: "D-HH:MM",
e.g. 1-00:00 = Sunday, 0:00 Uhr

Example

Actual date as per Real Time Clock: 08.12.

Input: =CL(0;0;0)<DD.MO.YY> Printout:08.12.

Input: =CL(2;1;0)<DD.MO.YY> Printout: 09.02.

Example for BBE date

Input: =CL(0;0;0;0;0;1;3;2;3;2)<DD.MO.YY>

At print start the calculated date is displayed at the printing system and can be modified (+/- 3 days and +/- 2 months):

Display: ID_1 DD:MO:YY
08.12.11

Example for rounded date

The beginning of the week is on Sunday (08.12.) at 00:00. The date of Monday should be printed the whole week.

Input: =CL(0;0;0;0;0;0;0;0;0;2;1-00:00)<DD.MO.YY>

Current date	Rounded date
07.12. 23:59:59	02.12.
08.12. 00:00:00	09.12
09.12.	09.12.
14.12. 23:59:59	09.12.
15.12. 00:00:00	16.12.

8.6 Format Identifier (Date & Time)

Standard format	
HH	Hours 2-digit (24 hours)
HE	Hours 2-digit (12 hours)
MI	Minutes 2-digit
SS	Seconds 2-digit
AM	AM/PM output
DD	Day 2-digit
MO	Month 2-digit
YYYY	Year 4-digit
YY	Year 2-digit
Y	Year 1-digit
WW	Calendar week
DW	Day of week (Sunday = 0)
DW1	Day of week (Sunday = 1)
DwX	Day of week An arbitrary ASCII character can be used for x, from which it is counted consecutively
DOWxxxxxx	Day of week - variable For x, any ASCII character can be used The first ,x' denominates Sunday, the next denominates Monday and so on until Saturday For each weekday a character must be created
DOY	Day of year 3-digit (First January = 1)
DY	Day of year 3-digit (First January = 0)
Examples	
DD.MO.YY	22.01.10
MO/DD/YYYY	01/22/2010
YY-MO-DD	10-01-22
YYMODD	100122

The format identifier 'HE' and 'AM'/'am'/'Am' are supplemented. Therefore the output of hours in 12-hours mode is possible. By the additional output of format identifier 'AM' the output of time in american/english format is possible.

Example

```
=CL(0;0;0;0)<HH:MI:SS>      --> 15:30:00
=CL(0;0;0;0)<HE:MI:SS>      --> 03:30:00
=CL(0;0;0;0)<HE:MI:SS AM>   --> 03:30:00 PM
=CL(0;0;0;0)<HE:MI:SS am>   --> 03:30:00 pm
=CL(0;0;0;0)<HE:MI:SS Am>   --> 03:30:00 p.m.
```

By separating the output of time and AM/PM output in 2 text fields, also the following output format is possible:

```
--> 03:30:00 pm
```

Extended format	
XMO	Name of month short
XSO	Name of month long
XSD	Weekday short
XLD	Weekday long
For X you can enter the country identification of desired language	
C = Canadian D = Danish E = English F = French G = German I = Italian N = Dutch O = Norwegian S = Spanish U = Finnish W = Swedish	
Examples:	
DD.EMO.YY	22.JAN.10
DD.ESO YYYY	22. January 2010
ELD,DD.GMO.YY	Friday, 22. JAN.10
ESD,DD.MO.YY	FR, 22.01.10

Extended format - XMO

C	JA	FE	MR	AL	MA	JN	JL	AU	SE	OC	NO	DE
D	JAN	FEB	MAR	APR	MAJ	JUN	JUL	AUG	SEP	OKT	NOV	DEC
E	JAN	FEB	MAR	APR	MAY	JUN	JUL	AUG	SEP	OCT	NOV	DEC
F	JAN	FEV	MAR	AVR	MAI	JUIN	JUIL	AOU	SEP	OCT	NOV	DEC
G	JAN	FEB	MRZ	APR	MAI	JUN	JUL	AUG	SEP	OKT	NOV	DEZ
I	GEN	FEB	MAR	APR	MAG	GIU	LUG	AGO	SET	OTT	NOV	DIC
N	JAN	FEB	MRT	APR	MEI	JUN	JUL	AUG	SEP	OKT	NOV	DEC
O	JAN	FEB	MAR	APR	MAI	JUN	JUL	AUG	SEP	OKT	NOV	DES
S	ENE	FEB	MAR	ABR	MAY	JUN	JUL	AGO	SEP	OCT	NOV	DIC
U	TAM	HEL	MAA	HUH	TOU	KES	HEI	ELO	SYU	LOK	MAR	JOU
W	JAN	FEB	MAR	APR	MAJ	JUN	JUL	AUG	SEP	OKT	NOV	DEC

Extended format - XSO

C	January	February	March	April	May	June
D	Januar	Februar	Marts	April	Maj	Juni
E	January	February	March	April	May	June
F	Janvier	Février	Mars	Avril	Mai	Juin
G	Januar	Februar	Maerz	April	Mai	Juni
I	Gennaio	Febbraio	Marzo	Aprile	Maggio	Giugno
N	Januari	Februari	Maart	April	Mei	Juni
O	Januar	Februar	Mars	April	Mai	Juni
S	Enero	Febrero	Marzo	Abril	Mayo	Junio
U	Tammikuu	Helmikuu	Maaliskuu	Huhtikuu	Toukokuu	Kesaekuu
W	Januari	Februari	Mars	April	Maj	Juni

C	July	August	September	October	November	December
D	Juli	August	September	Oktober	November	December
E	July	August	September	October	November	December
F	Juillet	Août	Septembre	Octobre	Novembre	Décembre
G	Juli	August	September	Oktober	November	Dezember
I	Luglio	Agosto	Settembre	Ottobre	Novembre	Dicembre
N	Juli	Augustus	September	Oktober	November	December
O	Juli	August	September	Oktober	November	Desember
S	Julio	Agosto	Septiembre	Octubre	Noviembre	Diciembre
U	Heinaekuu	Elokuu	Syyskuu	Lokakuu	Marraksuu	Joulukuu
W	Juli	Augusti	September	Oktober	November	December

Extended format - XSD

C	SUN	MON	TUE	WED	THU	FRI	SAT
D	SO	MA	TI	ON	TO	FR	LO
E	SUN	MON	TUE	WED	THU	FRI	SAT
F	DIM	LUN	MAR	MER	JEU	VEN	SAM
G	SO	MO	DI	MI	DO	FR	SA
I	DOM	LUN	MAR	MER	GIO	VEN	SAB
N	ZO	MA	DI	WO	DO	VR	ZA
O	SO	MA	TI	ON	TO	FR	LO
S	DOM	LUN	MAR	MIE	JUE	VIE	SAB
U	SU	MA	TI	KE	TO	PE	LA
W	SO	LA	TI	ON	TO	FR	LO

Extended format - XLD

C	Sunday	Monday	Tuesday	Wednesday	Thursday	Friday	Saturday
D	Søndag	Mandag	Tirsdag	Onsdag	Torsdag	Fredag	Lørdag
E	Sunday	Monday	Tuesday	Wednesday	Thursday	Friday	Saturday
F	Dimanche	Lundi	Mardi	Mercredi	Jeudi	Vendredi	Samedi
G	Sonntag	Montag	Dienstag	Mittwoch	Donnerstag	Freitag	Samstag
I	Domenica	Lunedì	Martedì	Mercoledì	Giovedì	Venerdì	Sabato
N	Zondag	Maandag	Dinsdag	Woensdag	Donderdag	Vrijdag	Zaterdag
O	Søndag	Mandag	Tirsdag	Onsdag	Torsdag	Fredag	Lørdag
S	Domingo	Lunes	Martes	Miércoles	Jueves	Viernes	Sábado
U	Sunnuntai	Maanantai	Tiistai	Keski-viikko	Torstai	Perjantai	Lauantai
W	Söndag	Måndag	Tisdag	Onsdag	Torsdag	Fredag	Lördag

8.7 Currency Variable

SOH	BM	[n]	=	C	U	(a	;	b	;	c	;	d	;	e	;	f	;	g)	t1	t2	t...	t70	ETB
-----	----	-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	----	----	------	-----	-----

= CU Signification of variable Euro
 a ANSI-Code of thousand separator as decimal figure
 b ANSI-Code of comma separator as decimal figure
 c Quantity of numbers after the comma as decimal figure
 d Operand A Before the processing the variable Euro
 e Operand B calculates the term
 f Operand C $\frac{A \times B}{C}$
 g Rounding format
 t1, t2, ... Format string, is indicated by "< >"

Example:

In case the contents of field 20 has to be converted from USD into EUR the definition of variable for the user defined format is as follows:

B01 '=CU(46;44;2;20;"1,0";"0,68861";"0,01")Result: <>Euro'
 B20 1.250,44 USD

Printout: 1.250,44 USD
 Result: 1.815,89 Euro'

* 1 USD = 0,68861 Euro (11.01.2010)

8.8 Shift Variable

```
SOH BM [n] = S H ( ) t1 t2 t... t70 ETB
```

= SH identification of shift variable



NOTICE!

The shift variable did not need any parameters. The settings for the output are defined with the corresponding parameter sets. (see above)

Beispiel

The shift times are defined: 00:00 - 11:59 "Shift1"
 12:00 - 23:59 "Shift2"
 =SH() Printout at 10:00 Uhr: "Shift1"
 =SH() Printout at 13:00 Uhr: "Shift2"

Set shift times

```
SOH F C I D - - r N N H H M M h h m m ETB
```

NN = ID [01 ... 24]
 HH = start hour
 MM = start minute
 hh = end hour
 mm = end minute

Get shift variable

```
SOH F C I D - - w N N p p p p p p p p p p ETB
```

Answer

```
SOH A N N H H M M h h m m p p p p p p p p ETB
```

Set shift text

```
SOH F C I E - - r N N T T T T T T T T T T ETB
```

NN = ID [01 ... 24]
 T = max. 10 characters

Get shift variable

```
SOH F C I E - - w N N p p p p p p p p ETB
```

Answer

```
SOH A N N ; T T T T T T T T T T ; p p p p p p p p ETB
```

8.9 User Guiding

SOH	BM	[n]	=	U	G	(c	;	t	;	m	;	ap	;	ae	;	sp)	t1	t2	t...	t70	ETB
-----	----	-----	---	---	---	---	---	---	---	---	---	---	----	---	----	---	----	---	----	----	------	-----	-----

= UG identification user guiding

c start position for the entry

t type of entry
 0 numerical
 1 alphanumerical

m mode of entry
 0 do not jump over special characters
 1 jump over special characters

ap alignment at printing
 0 aligned to the right side

ae alignment at entry
 0 aligned to the right side

sp prompt text for the variable, max. 24 characters
 The entry has to be included in ".

Example

Entry: =UG(1;0;0;0;0;"Enter article no.")<123456>
 Display: Enter article no.
 000000

8.10 User Guiding with Mask

```
SOH|BM|[n]=UM(c;t;m;ap;ae;sp;d;ma)t1t2t...t70|ETB
```

- = UM identification user guiding with mask
- c start position for the entry
- t type of entry (is ignored with existing mask definition)
 - 0 numerical
 - 1 alphanumerical
- m mode of entry (is ignored with existing mask definition)
 - 0 do not jump over special characters
 - 1 jump over special characters
- ap alignment at printing
 - 0 aligned to the right side
- ae alignment at entry
(always left aligned with existing mask definition)
 - 0 right aligned
 - 1 left aligned, cursor at the beginning of the text
 - 2 left aligned, cursor at the start position
 - 3 right aligned, remove fill characters
 - 4 left aligned, cursor at the beginning of the text,
remove fill characters
 - 5 left aligned, cursor at the start position,
remove fill characters
- sp prompt text for the variable, max. 24 characters
The entry has to be included in ".
 - 0 setpoint value remains at key entry (inserting mode)
 - 1 with first key press the setpoint value disappears
 - 2 setpoint value is retained (overwrite mode)
- d deleting setpoint value
 - 0 setpoint value remains at key entry (inserting mode)
 - 1 with first key press the setpoint value disappears
 - 2 setpoint value is retained (overwrite mode)
- ma definition of mask
possible mask characters are
 - 9 numbers only
 - # only numbers and leading signs
 - ? letters only
 - a alphanumeric characters (letters and numbers)
 - C any characters

Example

```
Entry: =UM(1;0;0;0;0;"Enter article no.";0;"999-aa")<123-xx>
Display: Enter article no.
         123-xx
```

8.11 Memory Card Data

```
SOH|BM|[n]|=MD|(FN="filename";SE='x';CH=x;SC="x";SF="x";RC="x")|ETB
```

= MD	identification of memory card data
FN	file name of table onto memory card with CSV data
SE	Separator sign (default = ';')
CH	column name in the first line (0 = no, 1 = yes)
SC	name and/or number of column that should be referenced
SF	field name and/or field index of field onto the layout, which contains the searched data
RC	name and/or number of column, which contains the data to be printed




NOTICE!

If in parameter SF a field name is indicated, this must have been defined for the appropriate field by an AC attribute statement!

Example

```
AC[1]NAME="FCODE"
BM[2]=MD(FN="a:\daten.csv";SE=';';CH=1;SC="Farbcode";SF="FCODE";
RC="IC-Nummer")
```

Field 1	Output Field 2
00001	121478242
23252	784587448



8.12 GS1-128 Parser



NOTICE!

By means of this variable type, the content of an application identifier in a GS1-128 bar code can be determined.

```
SOH|BM|[n]|=A|I|(p;Ai)|ETB
```

= AI	identification of GS1-128 parser
p	identification of the link element (field number)
Ai	application identifier

Example

```
Field 1 ="00123456789012345675"    GS1-128 with AI00
=Ai(1;"00")                        Printout: 123456789012345675
```

8.13 EPC Calculation (Electronic Product Code)

SOH BM [n] = E P C (M ; L ; F ; P ; N1 ; {N2}) ETB

- = EPC identification of EPC calculation
- M coding method
- L length of manufacturer number (company prefix)
- F filter value
- P verification of check digit
- N1 identification of link element (field number)
- N2 identification of link element (field number) - optional

For more information, visit the following web sites:
www.epcglobalinc.org or www.gs1.org

Param.	Value range		
M	0 = coding method SSCC96	3 = coding method GRAI96	
	1 = coding method SGTIN96	4 = coding method GIAI96	
	2 = coding method SGLN96		
L	6...12		
F	Coding	Filter value	Binary
	SSCC96	All Others	000
		Undefined	001
		Logistical / Shipping Unit	010
	SGTIN96	All Others	000
		Retail Consumer Trade Item	001
		Standard Trade Item Grouping	010
		Single Shipping/ Consumer Trade Item	011
	SGLN	All Others	000
		Physical Location	001
	GRAI	All Others	000
	GIAI	All Others	000
P	0 = no verification; 1 = verification		
N1, N2	any		

Example 1

Field 1 ="00123456789012345675" GS1-128 with AI00
 Field 2 =AI(1;"00") --> Printout: 123456789012345675
 Field 3 =EPC(0;12;0;1;2) --> Printout: 3100DA7557D32C38E7000000
 The EPC is calculated with the content of Field 2. The coding method SSCC96 is used. In Field 2 a valid NVE must be represented (18-digit, correct check digit).

Example 2

Field 1 ="4141234567890128254123" GS1-128 with AI00, AI254
 Field 2 =AI(1;"414") --> Printout: 1234567890128
 Field 3 =AI(1;"254") --> Printout: 123
 Field 4 =EPC(2;10;0;0;2;3) --> Printout: 3208499602D218000000007B
 The EPC is calculated with the content of Field 2 and Field 3. The coding method SGLN96 is used. In Field 2 a valid ILN must be represented (13-digit). In the example, Field 3 contains an optional serial number. No verification of check digit of ILN (8) is effected.

* only when using option RFID

8.14 Check Digit

SOH	BM	[n]	=	C	D	(d	;	s	;	l	;	t	;	w	;	m	;	r	;	o)	t1	t...	t70	ETB
-----	----	-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	----	------	-----	-----

- = CD Identification of check digit
- d Data for check digit calculation (field number of constant text)
Constant text is enclosed in "".
- s Start position within data
1 ...n Start calculation at digit x
- l Number of digits. If the parameter is not indicated, the remaining data (from start position) is used for the check digit calculation.
- t Check digit type
 - 0 Modulo 10 (weighting 3)
 - 1 Modulo 11
 - 2 Modulo 43
 - 3 Modulo 47 (weighting 15)
 - 4 Modulo 47 (weighting 20)
 - 5 Modulo 103
 - 6 Customized

Optional parameters for customized check digit

- w Weighting.
Constant text enclosed in "" - contains the individual weighting values or an interval.
Individual values: "x1,x2"
Interval: "x1...x2"
- m Modulo
- r Add result to
- o Print only one digit
 - 0 No
 - 1 Yes

Example

Entry: =CD("123456789012";0;0;0)
Printout: 8

Entry: =CD("1234567890";0;0;6;"1,3";10;10;1)
Printout: 5

8.15 Substring

SOH	BM	[n]	=	S	S	(d	;	s	;	l)	ETB
-----	----	-----	---	---	---	---	---	---	---	---	---	---	-----

= SS Identification of substring

d Data used for substring extraction (field number or field name or constant text.
Constant text is enclosed in "").

s Start position within data. If this parameter is omitted, the substring extraction starts with the 1st character of the data string.
1 n Start at digit x

l Number of digits. If this parameter is omitted, all characters from the start position to the end of the data string are returned.
1 ...n At the start position x digits

Example:

Entry: =SS("1234567890";4;3)
Printout: 456
Field "ARTIKELNR" has the contents "370012330295"

Entry: =SS(ARTIKELNR;1;4)
Printout: 3700

9 Parameter Sets

9.1 Layout Parameters

Set layout length in 1/100 mm

SOH F C C L - - r N N N N N N N N - ETB

N: value of layout length in 1/100 mm, 7 digit ASCII number

Get layout length in 1/100 mm

SOH F C C L - - w N N N N N N N N - ETB

Answer

SOH A N N N N N N N N - p p p p p p p p ETB

Set layout width in 1/100 mm

SOH F C C O - - r N N N N N N N N ETB

N: indication of layout width in 1/100 mm, 7 digit ASCII number

Get layout width in 1/100 mm

SOH F C C O - - w P P P P P P P P ETB

Answer

SOH A N N N N N N N N - p p p p p p p p ETB

Set X offset

SOH F C C E - - r V N N N - - - - ETB

V: pre-sign of offset (+ or -)

NNN: offset value, 3 digit ASCII number in 1/10 mm

Get X offset

SOH F C C E - - w p p p p p p p p ETB

Answer

SOH A V N N N - - - - p p p p p p p p ETB

Set layouts per cycle

SOH F C A D I - r N N - - - - - ETB

NN: number of layouts per cycle (01 ... 25)

Get layouts per cycle

SOH F C A D I - w p p p p p p p p ETB

Answer

SOH A N N - - - - - p p p p p p p p ETB

NN: current layouts per cycle

Set layout alignment

SOH F C C J - - r N - - - - - ETB

N: 0 = left
 N: 1 = centre
 N: 2 = right

Get layout alignment

SOH F C C J - - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set contrast

SOH F C A B - - r N N N - - - - - ETB

NNN: Indication of contrast in % (010 ... 200)
 It is necessary to transmit a 3 digit ASCII number

Get contrast

SOH F C A B - - w p p p p p p p p ETB

Answer

SOH A N N N - - - - - p p p p p p p p ETB

Set material

SOH F C D N C - r N N N N - - - - - ETB

NNNN: indication of material
 Type 1: paper
 Type 2: foil

Get material

SOH F C D N C - w p p p p p p p p ETB

Answer

SOH A N N N N - - - - - p p p p p p p p ETB

Set number of columns

SOH F C C H A - r N - - - - - ETB

N = number of columns (1 ... 9)

Get number of columns

SOH F C C H A - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set column width

SOH F C C H B - r N N N - - - - ETB

NNN: indication of column width in 1/10 mm (0 ... 999)

Get column width

SOH F C C H B - w p p p p p p p p ETB

Answer

SOH A N N N - - - - p p p p p p p p ETB

Set line number of layout (n digits)

SOH F B A A - - r N ETB

N: Indication of line number in ASCII (1, 10, 100, ...)

Get line number of layout

SOH F B A A - - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set flip layout

SOH F C D O - - r N - - - - - ETB

N: 0 = flip layout Off
N: 1 = flip layout On

Get flip layout

SOH F C D O - - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set layout rotation

SOH F C D N - - r X - - - - - ETB

X: 0 = rotate layout Off
X: 1 = rotate layout On

Get layout rotation

SOH F C D N - - w p p p p p p p p ETB

Answer

SOH A X - - - - - p p p p p p p p ETB

Set operating mode flip/rotate layout

SOH	F	C	D	S	-	-	r	N	-	-	-	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

N: 0 = flip/rotate layout at the centre point of layout

N: 1 = flip/rotate layout at the centre point of printhead

Get operating mode flip/rotate layout

SOH	F	C	D	S	-	-	w	p	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Answer

SOH	A	N	-	-	-	-	-	p	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

9.2 Device Settings

Set print position

SOH F C A D K - r N N N N N N - - ETB

NNNNN: print position in 1/10 mm (0120 ... 0900)

Get print position

SOH F C A D K - w p p p p p p p p p ETB

Answer

SOH A N N N N N N - - p p p p p p p p ETB

NNNNN: print position in 1/10 mm

Set operating mode

SOH F C A D O - r N - - - - - - - ETB

N: 0 = intermittent mode

N: 1 = continuous mode

After changing the operating mode, the module is re-started automatically.

Get operating mode

SOH F C A D O - w p p p p p p p p p ETB

Answer

SOH A N - - - - - - - p p p p p p p p ETB

Set transfer ribbon control On/Off

SOH F C D B - - r N M - - - - - - - ETB

N: 1 = transfer ribbon control Off

N: 0 = transfer ribbon control On

Get transfer ribbon control On/Off

SOH F C D B - - w p p p p p p p p p ETB

Answer

SOH A N M - - - - - - - p p p p p p p p ETB

Set field handling

SOH | F | C | D | K | - | - | r | N | - | - | - | - | - | - | - | - | ETB

N: 0 = field handling Off

N: 1 = graphic received

N: 2 = delete graphic

N: 3 = restore graphic

Get field handling

SOH | F | C | D | K | - | - | w | p | p | p | p | p | p | p | p | ETB

Answer

SOH | A | N | - | - | - | - | - | - | p | p | p | p | p | p | p | p | ETB

Set display language

SOH | F | C | D | I | - | - | r | N | - | - | - | - | - | - | - | - | ETB

N: 0 = German

N: 8 = Italian

N: 15 = not used

N: 1 = English

N: 9 = Danish

N: 16 = Ukrainian

N: 2 = French

N: 10 = Polish

N: 17 = Turkish

N: 3 = Spanish

N: 11 = Greek

N: 18 = Swedish

N: 4 = Finish

N: 12 = Hungarian

N: 19 = Norwegian

N: 5 = Czech

N: 13 = Russian

N: 20 = Estonian

N: 6 = Portuguese

N: 14 = Chinese

N: 21 = Romanian

N: 7 = Netherlands

Get display language

SOH | F | C | D | I | - | - | w | p | p | p | p | p | p | p | p | ETB

Answer

SOH | A | N | - | - | - | - | - | - | p | p | p | p | p | p | p | p | ETB

Set external print parameters

SOH | F | C | C | P | - | - | r | N | - | - | - | - | - | - | - | - | ETB

N: 0 = only parameter settings by interface for label length, gap length and label width are taken into consideration.

N: 1 = parameter settings by interface are processed

N: 2 = parameter settings by interface are not taken into consideration

Get external print parameters

SOH | F | C | C | P | - | - | w | p | p | p | p | p | p | p | p | ETB

Answer

SOH | A | N | - | - | - | - | - | - | p | p | p | p | p | p | p | p | ETB

Set Codepage

SOH F C C N - - r N - - - - - ETB

- N: 0 = Codepage 1252 West European (former ANSI)
- N: 1 = Codepage 437 English
- N: 2 = Codepage 850 Western European
- N: 3 - 8 = not used
- N: 9 = Codepage 852 Slavic
- N: 10 = Codepage 857 Turkish
- N: 11 = Codepage 1250 Central and East European
- N: 12 = Codepage 1251 Cyrillic
- N: 13 = Codepage 1253 Greek
- N: 14 = Codepage 1254 Turkish
- N: 15 = Codepage 1257 Baltic
- N: 16 = WGL4 (UTF-8 coded data transmission)

Please find the tables referring to the above mentioned character sets on www.carl-valentin.de/Downloads.

Get Codepage

SOH F C C N - - w p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set user guiding

SOH F C D U - - r N - - - - - ETB

- N: 0 = Off, no entries are possible but pre-set values are printed.
- N: 1 = On, the user has to enter a value for each variable or to confirm the pre-set values by pressing the enter key. This default value is set each time the print module is switched on
- N: 2 = Auto, the entries for a layout are repeated after each print and the last entered values are the new pre-set values.

Get user guiding

SOH F C D U - - w p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set keyboard layout

SOH F C C K - - r N - - - - - ETB

N: 0 = German
 N: 1 = English
 N: 2 = French
 N: 3 = Greek
 N: 4 = Spanish
 N: 5 = Swedish
 N: 6 = US American
 N: 7 = Russian

Get keyboard layout

SOH F C C K - - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set sound level of key click (buzzer)

SOH F C C B - - w p p p p p p p p ETB

N: 0 = Keyboard click (buzzer) Off
 N: 1-7 = Sound level of key click

Get sound level of key click (buzzer)

SOH F C C B - - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set hotstart On/Off

SOH F C D W - - r N - - - - - ETB

N: 0 = Off
 N: 1 = On

Get hotstart On/Off

SOH F C D W - - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set default layout On/Off

SOH F C M K E - r N - - - - - ETB

N: 0 = Off: Print start without layout definition signalises error.
 N: 1 = On: Default layout is printed without layout definition.
 Default: Off

Get default layout On/Off

SOH F C M K E - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set layout change confirmation

SOH F C S D F C r N - - - - - ETB

N: 0 = Confirmation Off
 N: 1 = Confirmation On

Get layout change confirmation

SOH F C S D F C w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set 'print after measuring'

SOH F C S D F D r N - - - - - ETB

N: 0 = Off
 N: 1 = On

Get 'print after measuring'

SOH F C S D F D w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

9.3 Interface

By means of the following commands the parameters of the serial interface can be set. Note that after sending one of the commands also the host computer changes the corresponding parameter of its interface to allow further communication of host computer-printing system. For all interface commands the interface is fixed with x. The following values are allowed:

x = 1 ⇒ COM 1

x = 2 ⇒ COM 2

In all other cases automatically the first serial interface is addressed. In the answers the addressed interface is also returned.

Set all interface parameters

```
[SOH]FCFFx-rm;b;p;d;s[ETB]
```

m = mode (0 = Off, 1 = On, 2 = On, without error message)

b = baud rate (2400, 4800, 9600, 19200, 38400, 115200)

p = parity (n = no parity, e = even parity, o = odd parity)

d = number of data bits (7, 8)

s = number of stop bits (1, 2)

Get all interface parameters

```
[SOH]FCFFx-wppppppp[ETB]
```

Answer

```
[SOH]Ax;m;b;p;d;s;pppppppp[ETB]
```

Example: activate interface COM1 and set 9600 Baud, no parity, 8 data bits, 2 stop bits
[SOH]FCFF1-r1;9600;n;8;2[ETB]

Interface protocol

There are two different interface protocols available. Usually SOH = 01_{Hex} and

ETB = 17_{Hex}. However there are host computers (e.g. AS/400), which cannot work with these characters. Therefore you can switch SOH = 5E_{Hex} and ETB = 5F_{Hex}. The host computer has to change the corresponding parameter as well.

Set SOH and ETB

```
[SOH]FCGC--rN-----[ETB]
```

N: 0 = SOH = 01_{Hex}, ETB = 17_{Hex}

N: 1 = SOH = 5E_{Hex}, ETB = 5F_{Hex}

Get SOH and ETB

```
[SOH]FCGC--Wppppppp[ETB]
```

Answer

```
[SOH]AN-----pppppppp[ETB]
```

N: 0 = SOH = 01_{Hex}, ETB = 17_{Hex}

N: 1 = SOH = 5E_{Hex}, ETB = 5F_{Hex}

N: 2 = other character combination

Data memory

Set data memory

SOH F C G D - - r M - - - - - - ETB

M: 0 = Off, after receiving FBCA0r or FBDA0r the interface is locked until the end of the print order, i.e. you cannot write more data in the receiving buffer.

M: 1 = Off, after receiving FBCA0r or FBDA0r the interface is locked until the end of the print order, i.e. you cannot write more data in the receiving buffer.

M: 2 = Extended, after starting a print order it is possible to write more data in the receiving buffer. These data is processed during the print and the next layout is prepared.

Get data memory

SOH F C G D - - W p p p p p p p p ETB

Answer

SOH A M - - - - - - p p p p p p p p ETB

Set reaction to unknown interrogative set

SOH F C G E A - r N - - - - - - ETB

N = value range between 0 and 3

Get reaction to unknown questions

SOH F C G E A - w p p p p p p P p ETB

Answer

SOH A N - - - - - - p p p p p p p p ETB

9.4 Network

```
SOH F C L A - - r C 0 A 8 0 0 1 5 ETB
```

All network parameter sets start in the third column with a 'L'. Column 4 shows the identification for the corresponding network parameter. Column 5 can show another sub-identification.

Because of the fact that the argument size is limited to 8 characters, the IP addresses (IP address, network mask, gateway address) which consist of 32 bit are transmitted in HEX presentation.

For all data which is transmitted in HEX presentation (also the MAC address) it is allowed to use capital as well as small letters.

In contrary to the parameter settings of the other interfaces, the settings of the following sets were saved immediately onto Flash, i.e. it is not necessary to save the currently set configuration before switching off the printing system so the modifications are still available after switching on.

So that the made modifications become active, also without printing system Reset it is necessary to transmit a corresponding Z set which effects a Reset of the network devices.

Set IP address (e.g. 192.168.0.21)

```
SOH F C L A - - r C 0 A 8 0 0 1 5 ETB
```

Get IP address

```
SOH F C L A - - w p p p p p p p ETB
```

Answer

```
SOH A C 0 A 8 0 0 1 5 p p p p p p p ETB
```

Set net mask (e.g. 255.255.255.0)

```
SOH F C L B - - r F F F F F F 0 0 ETB
```

Get net mask

```
SOH F C L B - - w F F F F F F 0 0 ETB
```

Answer

```
SOH A F F F F F F 0 0 p p p p p p p ETB
```

Set Gateway address (e.g. 192.168.0.1)

```
SOH F C L C - - r C 0 A 8 0 0 0 1 ETB
```

Get Gateway address

```
SOH F C L C - - w - - - - - - - ETB
```

Answer

```
SOH A C 0 A 8 0 0 0 1 p p p p p p p ETB
```


With the A record any address can be set in our pool.

With the C record any address in our pool and the identification of the MAC address can be set/changed at the same time.

Get MAC address

```
SOH F C L M B - w p p p p p p p p p ETB
```

```
SOH F C L M A - w p p p p p p p p p ETB
```

```
SOH F C L M C - w p p p p p p p p p ETB
```

Answer

```
SOH A 0 0 0 7 4 A - - p p p p p p p p ETB
```

```
SOH A 4 3 1 9 0 8 - - p p p p p p p p ETB
```

```
SOH A 0 0 0 7 4 A 4 3 1 9 0 8 p p p p p p p p ETB
```

NTP Server

NTP (Network Time Protocol) is a standardized Internet protocol permitting the synchronization of real-time clocks of network participants. The direct print module connects itself with a time server and align every 60 minutes its internal real-time clock with that of the time server in order to correct possible differences.

The address of server (IP address) can be freely configured in the printing system. The communication is effected by UDP and the fixed set port 123. The service in the direct print module is deactivated by transmitting the server address 0.0.0.0.

The time servers work together with the coordinated world time (UTC) and therefore an additional time shift is needed compared to the reference time. For Germany it is e.g. +1 hour.

The current state of the connexion can be queried with a status set.

Set NTP Server IP

```
SOH F C L N I - r N ETB
```

N: X.X.X.X (X = 0 ... 255)

Get NTP Server IP

```
SOH F C L N I - w p p p p p p p p p ETB
```

Answer

```
SOH A N N N N N N N N N p p p p p p p p ETB
```

0.0.0.0 deactivates the NTP service

Readout NTP status

SOH F C L N S - w p p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p p ETB

N: 0 = Off
 N: 1 = OK
 N: 2 = Error

Set time zone (hour offset)

SOH F C L N Z - r N ETB

N: -12, 12

Get time zone (hour offset)

SOH F C L N Z - w p p p p p p p p p ETB

Answer

SOH A N N N N N N N N N p p p p p p p p p ETB

Reset Network Device

SOH F C L Z - - r ----- ETB

For this set is no enquiry possible. This set causes that modifications made by the transfer of the previous sets become effective.

9.5 Sensors

Get condition of compressed air

```
SOH F C M B H - w p p p p p p p p ETB
```

Answer

```
SOH A N - - - - - p p p p p p p p ETB
```

N: 0 = no or not enough compressed air

N: 1 = compressed air OK

Get condition of cover

```
SOH F C M B I - w p p p p p p p p ETB
```

Answer

```
SOH A N - - - - - p p p p p p p p ETB
```

N: 0 = cover open

N: 1 = cover closed

9.6 Offset Values

Set X offset

```
SOH F C C E - - r V N N N - - - - ETB
```

V: offset prefix (+ or -)

NNN: offset value, 3 digit ASCII number in 1/10 mm

Get X offset

```
SOH F C C E - - w p p p p p p p p ETB
```

Answer

```
SOH A V N N N - - - - p p p p p p p p ETB
```

Set print offset

```
SOH F C A D L A r N N N N N - - M ETB
```

NNNNN: value of print offset

M: Unit - 0 = print offset in 1/10 mm (00000...99999)

1 = print offset in 1/10 ms (00000...99999)

Get print offset

```
SOH F C A D L A w p p p p p p p p ETB
```

Answer

```
SOH A N N N N N - - M p p p p p p p p ETB
```

NNNNN: value of print offset

M: Unit - 0 = print offset in 1/10 mm

1 = print offset in 1/10 ms

9.7 Service Functions

Set Online / Offline

SOH F C M K C - r M - - - - - ETB

M: 0 = Offline Off
 M: 1 = Offline On

Get Online / Offline

SOH F C M K C - w p p p p p p p p ETB

Answer

SOH A M - - - - - p p p p p p p p ETB

After changing by interface the display is automatically new initialized (by activated online/offline changing to online indication).

Set reprint action

SOH F C M K D - r N - - - - - ETB

Get reprint action

SOH F C M K D - w p p p p p p p p ETB

N: 0 = complete reprint
 N: 1 = empty reprint

Answer

SOH A N - - - - - p p p p p p p p ETB

Get position of printhead (close printhead)

SOH F C M B C - r N - - - - - ETB

N: 1 = printhead down (closed)

Get condition of printhead photocell

SOH F C M B C - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

N: 0 = printhead is open
 N: 1 = printhead is closed

Get position of printhead (open printhead)

SOH F C M B D - r N - - - - - ETB

N: 1 = printhead up (open)

Get condition of printhead photocell

SOH F C M B C - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

N: 0 = printhead is open
 N: 1 = printhead is closed

Get printhead temperature

SOH F C M C - - w p p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

NNN: value of temperature, 3 digit ASCII number in degrees

Set transfer ribbon length

SOH F C D Q A - r N N N N - - - - ETB

NNNN: value of transfer ribbon length in m

Possible entries: 300, 450, 600, 900 or 1000

Get transfer ribbon length

SOH F C D Q A - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set transfer ribbon prior warning

SOH F C M L A - r N - - - - - ETB

N: 0 = Off

N: 1 = On

Get transfer ribbon prior warning

SOH F C M L A - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p P p p p p ETB

Set diameter for transfer ribbon prior warning

SOH F C M L B - r N N N - - - - ETB

NNN: 030 ... 090 diameter in mm

Get transfer ribbon prior warning

SOH F C M L B - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Readout current transfer ribbon diameter

SOH F C M L C - w - - - - - - - ETB

Answer

SOH A N N N - - - - - p p p p p p p p ETB

Set mode for transfer ribbon prior warning

SOH F C M L D A r N - - - - - - - ETB

N: 0 = Warning

N: 2 = Error

Get mode for transfer ribbon prior warning

SOH F C M L D A w p p p p p p p p ETB

Answer

SOH A N - - - - - - - p p p p p p p p ETB

Set printhead resistance

SOH F C M G - - r N N N N N - - - ETB

NNNNN: value of resistance in Ohm.

Get printhead resistance

SOH F C M G - - w p p p p p p p p ETB

Answer

SOH A N N N N N - - - p p p p p p p p ETB

Set custom logo

SOH F C N R A - r N - - - - - - - ETB

N: 0 = Off

N: 1 = On

Get custom logo

SOH F C N R A - w p p p p p p p p ETB

Answer

SOH A N - - - - - - - p p p p p p p p ETB

Paper counter

The paper counter (kilometer value) of direct print module as well as of printhead can only be enquired by interface and not reset to 0.

Get paper counter of direct print module

```
SOH F C H A - - w p p p p p p p p ETB
```

Answer

```
SOH A N N N N N N N N N p p p p p p p p ETB
```

Get paper counter of printhead

```
SOH F C H B - - w p p p p p p p p ETB
```

Answer

```
SOH A N N N N N N N N N p p p p p p p p ETB
```

NNNNNNNN: kilometer value of printing system and/or printhead in meters (e.g. '00000123' = 123 m)

9.8 Date & Time**Set date**

```
SOH F C I A - - r D D M O Y Y D W ETB
```

DD = day of month

MO = month

YY = year

DW = day of week ('00' = Sunday)

Get date

```
SOH F C I A - - w p p p p p p p p ETB
```

Answer

```
SOH A D D M O Y Y D W p p p p p p p p ETB
```

Set time

```
SOH F C I B - - r H H M I S S A M ETB
```

HH = hours

MI = minutes

SS = seconds

AM = mode ('am' = 12 hours mode AM, 'pm' = 12 hours mode PM,

'—' = 24 hours mode)

Get time

```
SOH F C I B - - w p p p p p p p p ETB
```

Answer

```
SOH A H H M I S S A M p p p p p p p p ETB
```

Automatically adjust clock for daylight saving changes

Because of the fact that there is no world-wide regulation if and when a changing of time between summer and wintertime (normal time) in the individual countries takes place, we distinguish between the following four formats for the definition for beginning and end of summertime.

F 0:	European format start of summertime = last Sunday in March end of summertime = last Sunday in October W: week (1 = first, ..., 5 = last) WD: day of week (0 = Sunday, ..., 6 = Saturday) MM: month (01 = January, ..., 12 = December)
F 1:	Fix date with indication of year DD: day MM: month (01 = January, ..., 12 = December) YY: year
F 2:	Fix date without indication of year DD: day MM: month (01 = January, ..., 12 = December)
F 3:	Week day after day in month WD: day of week (0 = Sunday, ..., 6 = Saturday) DD: after day (only the first day is taken into consideration) MM: month (01 = January, ..., 12 = December)

Set automatically adjust clock for daylight saving changes

SOH F C I G - - r N - - - - - ETB

Get automatically adjust clock for daylight saving changes

SOH F C I G - - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

N: 0 = Automatically adjust clock for daylight saving changes Off
N: 1 = Automatically adjust clock for daylight saving changes On

Set beginning of summertime

F 0: SOH F C I H - - r F W ; W D ; M M ; H H ; M M ETB

F 1: SOH F C I H - - r F D D ; M M ; Y Y ; H H ; M M ETB

F 2: SOH F C I H - - r F D D ; M M ; H H ; M M ETB

F 3: SOH F C I H - - r F W D ; D D ; M M ; H H ; M M ETB

Get beginning of summertime

SOH F C I H - - w p p p p p p p p ETB

Answer

SOH A F W W D M M p p p p p p p p ETB

The answer depends on each set format.

Set end of summertime

F 0: SOH F C I I - - r F W ; W D ; M M ; H H ; M M ETB

F 1: SOH F C I I - - r F D D ; M M ; Y Y ; H H ; M M ETB

F 2: SOH F C I I - - r F D D ; M M ; H H ; M M ETB

F 3: SOH F C I I - - r F W D ; D D ; M M ; H H ; M M ETB

Get end of summertime

SOH F C I I - - w p p p p p p p p ETB

Answer

SOH A F W W D M M p p p p p p p p ETB

The answer depends on each set format.

Set time shifting

SOH F C I J - - r N N N - - - - ETB

NNN: minutes

Get time shifting

SOH F C I J - - w p p p p p p p p ETB

Answer

SOH A N N N p p p p p p p p ETB

9.9 Password

Set password

SOH F C K A - - r N N N N - - - - ETB

NNNN = input of password
4 digit ASCII number in mm (0000 ... 9999)

Get password

SOH F C K A - - w p p p p p p p p ETB

Answer

SOH A N N N N - - - - p p p p p p p p ETB

Set function group

SOH F C K B - - r A B C D E - - - - ETB

- A: Function menu
 - 0 = password Off
 - 1 = password On

- B: CF card
 - 0 = password Off
 - 1 = standard directory allowed
 - 2 = password On

- C: not assigned

- D: Printer guiding
 - 0 = password Off
 - 1 = not assigned
 - 2 = Password On

- E: Favorites menu
 - 0 = password Off
 - 1 = password On

Get function group

SOH F C K B - - w p p p p p p p p ETB

Answer

SOH A a b c d e - - - - p p p p p p p p ETB

Set password function menu

SOH F C K D A - r N N N N - - - - ETB

NNNN = input of password
4 digit ASCII number in mm (0000 ... 9999)

Get password function menu

SOH F C K D A - w p p p p p p p p p ETB

Answer

SOH A N N N N - - - - p p p p p p p p ETB

Set password favorites menu

SOH F C K D B - r N N N N - - - - ETB

NNNN = input of password
4 digit ASCII number in mm (0000 ... 9999)

Enquire password favorites menu

SOH F C K D B - w p p p p p p p p p ETB

Answer

SOH A N N N N - - - - p p p p p p p p ETB

Set password memory card

SOH F C K D C - r N N N N - - - - ETB

NNNN = input of password
4 digit ASCII number in mm (0000 ... 9999)

Get password memory card

SOH F C K D C - w p p p p p p p p p ETB

Answer

SOH A N N N N - - - - p p p p p p p p ETB

Set password printing manually

SOH F C K D D - r N N N N - - - - ETB

NNNN = input of password
4 digit ASCII number in mm (0000 ... 9999)

Get printing manually

SOH F C K D D - w p p p p p p p p p ETB

Answer

SOH A N N N N - - - - p p p p p p p p ETB

9.10 Compact Flash Card

Save a layout onto Compact Flash card

SOH F M A O - - r P ETB

- O: In case a layout with the entered name exists already then the layout is overwritten without an enquiry. If you enter another value as 0, an enquiry appears demanding if you want to overwrite.
- P: File name of the layout which is to save. Drive and path name are optional, i.e. the file name is allowed to have more than 8 characters but is limited to 79.

Load a file from Compact Flash card

SOH F M B - - - r P ETB

- P: File name of the layout which is to load. Drive and path name are optional, i.e. the file name is allowed to have more than 8 characters but is limited to 79.

Delete a layout from Compact Flash card

SOH F M C - - - r P ETB

- P: File name of the layout which is to delete. Drive and path name are optional, i.e. the file name is allowed to have more than 8 characters but is limited to 79.

Format Compact Flash card

SOH F M D - - - r P ETB

- P: Optional drive identification with colon (e.g. A:).
In case no drive is indicated, then the currently selected is formatted.

Readout contents of CF card

SOH F M G O - - r P ETB

- O: In case O is indicated, no error messages are displayed at the printing display e.g. if no card is inserted.
- P: Optional drive identification with colon (e.g. A:).
In case no drive is indicated, then the currently selected is read out.

Answer

SOH File name/directory name ETB

- A list of all file entries is indicated, each entry is included in (SOH) and (ETB).

Readout free memory space

SOH F M H O - - w X p p p p p p p p ETB

O: In case O is indicated, no error messages are displayed at the printing display e.g. if no card is inserted.

X = Drive [A,B] (optional)

Answer

SOH A X n n n n - - - p p p p p p p p ETB

X = Drive [A,B]

n = Memory space in KB

Create directory

SOH F M I O - - r P ETB

O: In case a layout with the entered name already exists, then it is overwritten without an enquiry.

If you enter another value as O, an enquiry appears demanding if you want to overwrite.

P = Drive and path indication

Delete directory

SOH F M J - - - r P ETB

P = Drive and path indication

**NOTICE!**

The current directory cannot be deleted.

Delete directory path

SOH F M J A - - - r P ETB

Deletes the indicated directory including all containing sub-directories and files.

Change standard directory

SOH F M K - - - r P ETB

P = Drive and path indication

Readout current directory

SOH F M K - - - w ETB

Answer

SOH A P ETB

P = Current directory

Set standard directory for file selection via I/O

SOH F M K B - - r N ETB

N = directory path

Get standard directory for file selection via I/O

SOH F M K B - - w p p p p p p p p ETB

Antwort

SOH A N - - - - - p p p p p p p p ETB

Transfer file from printing system

SOH F M L - - - w P ETB

P: File name of file which is to transfer. Drive name and path name are optional, i.e. the file name is allowed to have more than 8 characters but is limited to 79.

Answer

SOH A F * S ETB Data

F = File name
S = File size in Byte
Data = Binary data

Enquiry if the file exists

SOH F M M - - - w P ETB

P: File name of file which is to transfer. Drive name and path name are optional, i.e. the file name is allowed to have more than 8 characters but is limited to 79.

Answer

SOH A X P ETB Daten

X: 0 = File does not exist
1 = File exists
P = File name

Readout size of Compact Flash card

SOH F M P O - - w X ETB

O: In case O is indicated, no error messages are displayed at the printing display e.g. if no card is inserted.
X: Drive [A,B] (optional)

Answer

SOH A D n n n n - - - X ETB

X = Drive [A,B]
n = Memory in KB
D = enquired drive

Get drive status

SOH	F	M	S	-	-	-	w	X	ETB
-----	---	---	---	---	---	---	---	---	-----

X - Drive [A,B]

Answer

SOH	A	X	S	ETB
-----	---	---	---	-----

X = Drive [A,B]

S = Status

0: no storage medium

1: not formatted

2: ready

3: not determinable

9.11 Printing

Set number of lines (n digits)

SOH F B A A - - r N ETB

N = number of lines in ASCII (1, 10, 100, ...)

Get number of lines

SOH F B A A - - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Start/Stop Command

In addition to the actual start/stop command, the print order can also be interrupted via the parameter/remote record.

SOH F D - - - - r N - - - - - ETB

- N: 0 = stop printing
- N: 1 = continue printing
- N: 2 = cancel print order if it is already stopped

Reset error

Reset error

SOH F C M H - - r N N N N - - - - ETB

NNNN: current error ID or '9999'

Get error

SOH F C M H - - w p p p p p p p p ETB

Answer

SOH A N N N N 0 0 0 0 p p p p p p p p ETB

Get error ID and error text

SOH F C M H A - w p p p p p p p p ETB

Answer

SOH A N N N N ; error text ; p p p p p p p p ETB

Item number of print order

By means of this command the Host computer can enquire following item numbers:

Total number of current print order

SOH	F	B	B	A	-	-	w	p	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Number of layouts which are still to print

SOH	F	B	B	B	-	-	w	p	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Number of already printed layouts

SOH	F	B	B	C	-	-	w	p	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

At the end of one of these commands the printing system returns the corresponding number as ASCII value (4 res. 5 digits) in the answer set.

Answer

SOH	A	N	N	N	N	-	-	-	-	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

With this set it is also possible to transmit the item number of print order to the printing system.

Item number of print order

SOH	F	B	B	A	-	-	r	N	N	N	N	N	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

NNNNN = 5 digits item number of order

Interval in cutter mode

SOH	F	B	B	D	-	-	r	N	N	N	N	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

NNNNN: interval

Start printing

SOH	F	B	C	-	-	-	r	S	-	-	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

This command starts the print order which is actually set in the printing system. The current parameters such as print mode, speed, initialization etc. are used.

S = x: sorted (e.g. pages 1-5, then again 1-5 etc. are printed)
 S = 1: unsorted (page 1 is printed x times, then page 2 x times, etc.)

SOH	F	B	E	-	-	-	r	n	n	n	n	n	n	n	n	n	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

With this command the printjob identifier which appears in "printing" res. "stopped" window is assigned to a print order. If only blanks are transmitted, then the printjob identifier is deleted and the display shows "noname".

Initialization of page handling

SOH	F	B	F	-	-	-	r	ETB
-----	---	---	---	---	---	---	---	-----

Selection of current page

SOH	F	B	G	-	-	-	r	P	ETB
-----	---	---	---	---	---	---	---	---	-----

P = current page number [1 ... 9]

Select order of pages to be printed

SOH	F	B	H	-	-	-	r	P ₁	P ₂	P ₃	ETB
-----	---	---	---	---	---	---	---	----------------	----------------	----------------	-----

P₁; P₂;... = pages to be printed

Generation of page without print start

SOH	F	B	I	-	-	-	r	S	ETB
-----	---	---	---	---	---	---	---	---	-----

With this command the corresponding page is only generated, i.e. no print start signal is sent.

S = x: sorted (e.g. pages 1-5, then again 1-5 etc. are printed)
 S = 1: unsorted (page 1 is printed x times, then page 2 x times, etc.)

Feed**Parameter set to release a feed**

SOH	F	E	-	-	-	-	r	-	-	-	-	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Ribon feed**Parameter set to release a ribbon feed**

SOH	F	E	B	-	-	-	r	d	;	v	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Direct Coder: Ribbon feed with indication of distance and speed

d: Distance in mm

v: Speed in mm/s

Test print**Parameter set to release a test print**

SOH	F	F	-	-	-	-	r	-	-	-	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Status print**Parameter set to print a status print**

SOH	F	C	M	Q	-	-	r	N	-	-	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

N: 0 = settings

N: 1 = bar codes

N: 2 = fonts

Cancel print orders**Parameter set to cancel all active print orders**

SOH	F	G	A	-	-	-	r	N	-	-	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

N: - = Cancel active print orders and delete all layout data

N: 1 = Cancel active print orders and receive new layout data

With the execution of this command:

- possible upcoming errors are confirmed
- possible upcoming customized entries are cancelled

9.12 Emulation

Set emulation

SOH	F	Z	-	-	-	-	r	N	-	-	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

N: 0 = CVPL (Carl Valentin Programming Language)

N: 1 = ZPL II® (Zebra Programming Language)

Enquire emulation

SOH	F	Z	-	-	-	-	w	p	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Answer

SOH	A	N	-	-	-	-	-	p	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

10 Parameter Sets for C Mode

10.1 Machine Parameters

Set operating mode

SOH F C D C - - r N - - - - - - ETB

- N: 1 = external I/O static
- N: 3 = external I/O static continuous
- N: 5 = external I/O dynamic
- N: 6 = external I/O dynamic continuous

Get operating mode

SOH F C D C - - w p p p p p p p p ETB

Answer

SOH A N - - - - - - p p p p p p p p ETB

Set print offset

SOH F C A D L A r N N N N N - - M ETB

- NNNNN: print offset value
- M: unit - 0 = print offset in 1/10 mm (00000 ... 09999)
- 1 = print offset in 1/10 ms (00000 ... 99999)

Get print offset

SOH F C A D L A w p p p p p p p p ETB

Answer

SOH A N N N N N - - M p p p p p p p p ETB

- NNNNN: print offset value
- M: unit - 0 = print offset in 1/10 mm
- 1 = print offset in 1/10 ms

Set material speed at print start signal

SOH F C A D U D r N - - - - - - ETB

- N: 0 = Off
- N: 1 = On

Get material speed at print start signal

SOH F C A D U D w p p p p p p p p ETB

Answer

SOH A N - - - - - - p p p p p p p p ETB

- N: 0 = Off
- N: 1 = On

Set encoder resolution

SOH	F	C	A	D	U	A	r	N	N	N	N	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

N: value of encoder resolution (0100...9999)

Get encoder resolution

SOH	F	C	A	D	U	A	w	p	p	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Answer

SOH	A	N	N	N	N	-	-	-	-	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Set material feed per encoder turn

SOH	F	C	A	D	U	B	r	N	N	N	N	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

N: value of material feed in mm (0010 ... 9999)

Get material feed per encoder turn

SOH	F	C	A	D	U	B	w	p	p	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Answer

SOH	A	N	N	N	N	-	-	-	-	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Get material speed

SOH	F	C	A	D	U	C	w	p	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

By means of this command set it is possible to enquire material speed in mm/s. Please note that it is only possible to enquire the value and not to set.

Answer

SOH	A	N	N	N	N	-	-	-	-	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

10.2 Ribbon Save

Set ribbon save mode

SOH F C D R A - r N - - - - - ETB

- N = 0: Aus
- N = 1: Standard
- N = 2: Stage 2
- N = 3: Manually

Get ribbon save mode

SOH F C D R A - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set synchronisation of transfer ribbon and printhead

SOH F C D R B - r N N N - - - - - ETB

NNN: Value of synchronization in % (000-100)

Get synchronization of transfer ribbon and printhead

SOH F C D R B - w p p p p p p p p ETB

Answer

SOH A N N N - - - - - p p p p p p p p ETB

Set time for printhead move down

SOH F C D R C A r N N N N - - - - - ETB

NNNN: value of time for printhead move down in ms (0000 ... 9999)

Get time for printhead move down

SOH F C D R C A w p p p p p p p p ETB

Answer

SOH A N N N N - - - - - p p p p p p p p ETB

Set feedback distance

SOH F C D R F A r N N N N - - - - - ETB

NNNN: distance in mm

Get feedback distance

SOH F C D R F A w p p p p p p p p ETB

Answer

SOH A N N N N - - - - - p p p p p p p p ETB

Set feedback speed

SOH F C D R F B r N N N N - - - - ETB

NNNN: feedback speed in mm/s

Get feedback speed

SOH F C D R F B w p p p p p p p p ETB

Answer

SOH A N N N N - - - - p p p p p p p p ETB

Set power of transfer ribbon motor

SOH F C D R D A r N N N - - - - - ETB

NNN: value of transfer ribbon motor power in % (010 ... 200)

Get power of transfer ribbon motor

SOH F C D R D A w p p p p p p p p ETB

Answer

SOH A N N N - - - - - p p p p p p p p ETB

Set brake power for acceleration and braking

SOH F C D R E A r N N N - - - - - ETB

NNN: value of brake power for acceleration and braking
in % (000 ... 200)**Get brake power for acceleration and braking**

SOH F C D R E A w p p p p p p p p ETB

Answer

SOH A N N N - - - - - p p p p p p p p ETB

Set brake power during printing

SOH F C D R E B r N N N - - - - - ETB

NNN: value of brake power during printing in % (000 ... 200)

Get brake power during printing

SOH F C D R E B w p p p p p p p p ETB

Answer

SOH A N N N - - - - - p p p p p p p p ETB

10.3 I/O Parameters

Set IN signal level

SOH F C M D C - r 1 2 3 4 5 6 7 8 ETB

1-8 (inputs 1-8): 2 = increased and decreased
 1 = increased
 0 = decreased
 s = I/O signal by interface
 x = I/O signal blocked

Get signal level

SOH F C M D C - w p p p p p p p p ETB

Answer

SOH A 0 1 2 3 4 5 6 7 p p p p p p p p ETB

Set OUT signal level

SOH F C M D D - r 1 2 3 4 5 6 7 8 ETB

1-8 (outputs 1-8): 1 = signal level 1
 0 = signal level 0
 s = I/O signal by interface
 x = I/O signal blocked

Get OUT signal level

SOH F C M D D - w p p p p p p p p ETB

Answer

SOH A 0 1 2 3 4 5 6 7 p p p p p p p p ETB

Set software input

SOH F C M D F - r 1 2 3 4 5 6 7 8 ETB

1-8 (inputs 1-8): 1 = set software input
 0 = delete software input
 - = not considering software input
 P = pulse, execute software input once

Example: Auslösen eines Startimpulses = FCMDF-rP-----

Get current status of software inputs

SOH F C M D F - w p p p p p p p p ETB

Answer

SOH A 0 1 2 3 4 5 6 7 p p p p p p p p ETB

Set software output

SOH F C M D G - r 1 2 3 4 5 6 7 8 ETB

1-8 (outputs 1-8): 1 = set software output
0 = delete software output

Set start signal delay

SOH F C S D D - r N N N - - - - ETB

NNN: start signal delay in 1/100 s (0 ... 999)

Get start signal delay

SOH F C S D D - w p p p p p p p p ETB

Answer

SOH A N N N - - - - p p p p p p p p ETB

Set cancel continuous print (operating mode)

SOH F C S D F A r N - - - - - - ETB

N: 0 = Offs

N: 1 = On

Get cancel continuous print (operating mode)

SOH F C S D F A w p p p p p p p p ETB

Answer

SOH A N - - - - - - p p p p p p p p ETB

Set output signal 'print ready' active

SOH F C S D J - r N - - - - - - ETB

N: 0 = Off; at print start the 'print ready' signal is inactive.

N: 1 = On; at print start the 'print ready' signal remains active.

Get output signal 'print ready' active

SOH F C S D J - w p p p p p p p p ETB

Answer

SOH A N - - - - - - p p p p p p p p ETB

N: current setting (see above)

11 Parameter Sets for I Mode

11.1 Machine Parameters

Set operating mode

SOH F C A D H - r N - - - - - ETB

N: 1 = process single items
 N: 2 = continuous

Get operating mode

SOH F C A D H - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

N: current operating mode

Set print speed

SOH F C A A - - r N N N - - - - - ETB

NNN: Indication of print speed in mm/s
 It is necessary to transmit a 3 digit ASCII number.

Get print speed

SOH F C A A - - w p p p p p p p p ETB

Answer

SOH A N N N - - - - - p p p p p p p p ETB

Set back speed

SOH F C A D G - r N N N - - - - - ETB

NNN: indication of back speed in mm/s (050 ... 400)

Get back speed

SOH F C A D G - w p p p p p p p p ETB

Answer

SOH A N N N - - - - - p p p p p p p p ETB

NNN: current back speed

Set print offset

SOH F C A D L - r N N N N - - - - ETB

NNNN: print offset in 1/10 mm (0000 ... 9999)

Get print offset

SOH F C A D L - w p p p p p p p p ETB

Answer

SOH A N N N N N - - - - p p p p p p p p ETB

NNNN: current print offset

Set ribbon save On/Off

SOH F C D J - - r N - - - - - - - - ETB

N: 0 = Off

N: 1 = On

Get ribbon save On/Off

SOH F C D J - - w p p p p p p p p ETB

Answer

SOH A N - - - - - - - - p p p p p p p p ETB

11.2 I/O Parameters

Set IN signal level

SOH F C M D C - r 1 2 3 4 5 6 7 8 ETB

1-8 (inputs 1-8): 2 = increased and decreased
 1 = increased
 0 = decreased
 s = I/O signal by interface
 x = I/O signal blocked

Get signal level

SOH F C M D C - w p p p p p p p p ETB

Answer

SOH A 0 1 2 3 4 5 6 7 p p p p p p p p ETB

Set OUT signal level

SOH F C M D D - r 1 2 3 4 5 6 7 8 ETB

1-8 (outputs 1-8): 1 = signal level 1
 0 = signal level 0
 s = I/O signal by interface
 x = I/O signal blocked

Get OUT signal level

SOH F C M D D - w p p p p p p p p ETB

Answer

SOH A 0 1 2 3 4 5 6 7 p p p p p p p p ETB

Set I/O protocol port

SOH F C M D E - r T C P - - - - ETB

Port: Off
 COM1
 COM2
 TCP

Get I/O protocol port

SOH F C M D E - w p p p p p p p p ETB

Answer

SOH A 0 1 2 3 - - - - p p p p p p p p ETB

Set software input

SOH	F	C	M	D	F	-	r	1	2	3	4	5	6	7	8	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

1-8 (inputs 1-8): 1 = set software input
 0 = delete software input
 - = not considering software input
 P = pulse, execute software input once

Example: Enter a start impulse = FCMDF-rP-----

Get current status of software inputs

SOH	F	C	M	D	F	-	w	p	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Antwort

SOH	A	0	1	2	3	4	5	6	7	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Set software output

SOH	F	C	M	D	G	-	r	1	2	3	4	5	6	7	8	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

1-8 (outputs 1-8): 1 = set software output
 0 = delete software output

Set debounce start signal

SOH	F	C	S	D	C	-	r	N	N	N	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

NNN: debounce time start signal in ms (0 ... 100)

Get debounce start signal

SOH	F	C	S	D	C	-	w	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Answer

SOH	A	N	N	N	-	-	-	-	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Set start signal delay

SOH	F	C	S	D	D	-	r	N	N	N	-	-	-	-	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

NNN: start signal delay in 1/100 s (0 ... 999)

Get start signal delay

SOH	F	C	S	D	D	-	w	p	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Answer

SOH	A	N	N	N	-	-	-	-	p	p	p	p	p	p	ETB
-----	---	---	---	---	---	---	---	---	---	---	---	---	---	---	-----

Get cancel continuous print (operating mode)

SOH F C S D F A w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

Set output signal 'print ready' active

SOH F C S D J - r N - - - - - ETB

N: 0 = Off; at print start the 'print ready' signal is inactive.

N: 1 = On; at print start the 'print ready' signal remains active.

Get output signal 'print ready' active

SOH F C S D J - w p p p p p p p p ETB

Answer

SOH A N - - - - - p p p p p p p p ETB

N: current setting (see above)

12 Configuration & Status

Save configuration permanent

In case you want to save the described settings permanent into the printing system, then you have to transmit the following command to the printing system.

```
SOH F X - - - - r N - - - - - - - - ETB
```

N: 0 = save current parameter
 N: 1 = set all parameters to default values
 Then the print module performs a restart

Read configuration

```
SOH F X - - - - w - - - - - - - - ETB
```

The printing system sends as answer all current settings as parameter sets.

Status enquiry

Host computer can receive information about the printing system by the serial interface.

The status enquiry has the following data format:

```
SOH S ETB
```

Status return information

After receiving the status enquiry the printing system sends the corresponding status return information.

Data format of status enquiry

```
SOH 1. Byte          2. Byte          5.-1. digit ETB
      8 7 6 5 4 3 2 1 8 7 6 5 4 3 2 1
```

1. Byte	=	1. Status byte
		8. Bit = free
		7. Bit = always set
		6. Bit = free
		5. Bit = 1 = running print order 0 = no. of items (0 = no print order)
2. Byte	=	4. Bit = 1 = press stop key 0 = not pressed stop key
		3. Bit = cutter error (0 = no error; 1 = error)
		2. Bit = layout material (0 = no error; 1 = error)
		1. Bit transfer ribbon (0 = no error; 1 = error)
		2. Status byte
5.-1. digit	=	8. - 4. Bit = free
		3. Bit = Compact Flash card
		2. Bit = Mask set 1. Bit = Printhead temperature
		number of pieces with 5 digits as ASCII characters min. '00000' / max. '65535'

12.1 Autostatus

The direct printing systems are equipped with an auto status function, i.e. in certain operating modes the printing system actively sends the corresponding status. This can be enquired by the serial interface.

To activate the auto status, the host computer has to send the following command to the printing system:

```
SOH G 1. Byte 2. Byte ETB
```

Each of the below indicated message which is observed and send by the printing system has to be transmitted with a set Bit (see table below 1. Byte and 2. Byte) to the printing system by means of auto state function. The printing system sends after each performed condition the corresponding message (answer) to the host computer.

The following messages are provided:

1 Start of generation

2 End of generation

The printing system sends this state in case data for a complete layout was generated. The test print was not taken into consideration.

For counters/date variables the printing system sends for each layout a status cycle (start, end).

3 Start of printing

4 End of printing

The start of the print is send in case the generated data is send.

The end of the print is send in case the print of the layout is finished and the motor has stopped.

5 Start of cutting

6 End of cutting

This status describes the cutting. It can be checked for timeout and the end of the cut movement → error.

7 Start of feeding

8 End of feeding

This status is send in case an additional feeding (dispenser, cutter, tear off) is released.

9 Start of a print order

10 End of print order

This status signalizes the start and end of a complete print order (1...99999 layouts). This status is active in all operating modes.

11 Error

This status message is send in case an error occurs.

12 Printing stopped

This message is send if the printing is stopped.

13 Printing resumed

This message is send if the printing is resumed.

The printing system sends the auto status in the following format to the host computer:

SOH	G	1. Byte	2. Byte	ETB
-----	---	---------	---------	-----

1. Byte

- | | |
|------------------------------|------------------------|
| 8. Bit = start of generation | 4. Bit = start cutting |
| 7. Bit = end of generation | 3. Bit = end of cut |
| 6. Bit = start printing | 2. Bit = start feeding |
| 5. Bit = end of print | 1. Bit = always 0 |

2. Byte

- | | |
|-------------------------------|---------------------------|
| 8. Bit = end of layout feed | 4. Bit = free |
| 7. Bit = start of print order | 3. Bit = Printing stopped |
| 6. Bit = end of print order | 2. Bit = Printing resumed |
| 5. Bit = error | 1. Bit = always 0 |



NOTICE!

Bit 1 has to be in 1. Byte and 2. Byte always 0, otherwise the printing system possibly could recognize SOH or ETB.

At the status message of the printing system to the host computer always at least 1 Bit is set. However, it could be occur that several Bits are set at the same time.

At the status demand of the host computer to the printing system it is also possible that several Bits are set at the same time.

The auto status demand is saved in the printing system, i.e. it is set to 0 after switching off/on. Therefore it is necessary to demand it anew after each time the printing system is switched on.

Example

The printing system should observe the start of a print order. For this the host computer sends the following demand to the printing system.

SOH	G	00000000	01000000	ETB
-----	---	----------	----------	-----

After the condition is fulfilled (= start of the print order) the printing system sends the following message to the host computer:

SOH	G	00000000	01000000	ETB
-----	---	----------	----------	-----

With regard to the contents the answer corresponds always to the format set.

13 Monitored Printing

This protocol replaces the outdated Autostatus. In contrary to the Autostatus, this is not a binary protocol but a text-based protocol sending the commands as English clear text. The advantage is a very fast and simple error tracing and development. The disadvantage of a larger data volume plays nowadays a smaller role.

13.1 Short Introduction

In order to activate monitored printing:

(SOH)FHM---rSE(ETB)

(SOH)FHA---r2(ETB)

13.2 Parameter Sets (Host – Printer)

Formatting: # - SOH * - ETB

Command: Set monitoring mode.

Syntax: #FHM---rSEPnnnCnFn*

Example: #FHM---rSP10E*

Description: Activates the forwarding of certain events to the server.

The results are:

S - (start/stop): print start, print end, stop printing, continue printing, cancel printing.

E – (error): Error occurred, error confirmed.

C – (photocell): Activates the photocell test (n=1)/disable (n=0)

F – Activates the encoder profile (n=1)/disable (n=0)

P – (progress): Print progress, indicates the number of already printed labels. In standard case, the interval between two events is a label. If a number behind the flag is indicated, an event every *nnn* labels is released (see example). With column printing the event is released, as soon as the entered interval was reached or exceeded for the first time (example: 3 columns, interval 4, 20 labels in total. Event at label 6,9,12 and 18).

Command: Activate, disable the monitoring.

Syntax: #FHA---rn*

Example: #FHA---r2*

Description: activated, deactivates the monitoring (n=[0,2]);

,0' – enables the monitoring after completion of print order,

,1' – reserved

,2' – activates the monitoring for the current port.

13.3 Direct Enquiry

Command: Requests print status.

Syntax: #FHS---r*

Example: #FHS---r*

Description: Invites the client to send the current status.

Command: User command to the sender of print order.

Syntax: #FHU---rData*

Example: #FHU---rSE*

Description: Sends #Data* to the sender of print order.
Max 100 characters.

13.4 Answer Sets (Printer – Host)

Event: Print start

Set: #HSStart-*Pagename-Labelsrequested**

Example: #HSStart-NoName1-100*

Description: Indicates the start of a print order, including page name and number of labels to be printed.

Event: Printing completed

Set: #HSDone-*Pagename-Labelsprinted**

Example: #HSDone-NoName1-100*

Description: Indicates the completion of a print order including page name and number of printed labels.

Event: Printing stopped

Set: #HSHold-*Pagename-Labelsprinted**

Example: #HSHold-NoName1-10*

Description: Indicates the stopping of print order including page name and number of printed labels. Occurs when the user stopped the print order and/or after occurrence of an error.

Event: Continue printing

Set: #HSContinue-*Pagename-Labelsprinted**

Example: #HSContinue-NoName1-55*

Description: Indicates the continuation of print order including page name and number of printed labels. Occurs when the user restarts the print order.

Event: Cancel printing

Set: #HSAborted-*Pagename-Labelsprinted**

Example: #HSAborted-NoName1-57*

Description: Indicates the cancelation of printing including page name and number of printed labels.


Event: Error**Set:** #HSError-*Pagename-Labelsprinted-ErrorID-Errormessage****Example:** #HSError-NoName1-57-28-Messerfehler***Description:** Indicates the occurrence of an error including page name, number of printed labels, error ID and error text.**Event:** Error confirmation at printer**Set:** #HSAck-*Pagename-Labelsprinted* ***Example:** #HSAck-NoName1-57***Description:** Indicates the confirmation of an error including page name and number of printed labels.**Event:** Print progress**Set:** #HSProgress-*Pagename-Labelsprinted* ***Example:** #HSProgress-NoName1-60***Description:** Indicates the progress of print order including page name and number of printed labels. This event is also returned as answer to status enquiry, if the printer is printing.**Event:** Photocell value**Set:** #HSPhotocell-DLS:xxx-RLS:xxx***Example:** #HSPhotocell-DLS:3.8-RLS:1.9***Description:** Returns the values of transmission and reflexion photocell. The verification takes place every 5 ms; only changes are sent.**Event:** Encoder profile**Set:** # HSEnc-Dist:xxx-Speed:xxx***Example:** # HSEnc-Dist:120-Speed:202***Description:** Generates the profile of speed development of the packaging machine during a print order.**Event:** Answer to status enquiry (#FHS---r*)**Description:** The respective current print event is returned.

13.5 Sample Label

A simple label with monitoring of all parameters with output of the progress – all 10 labels could look as following:

```
FHM---rSP10E
//Ueberwachung einschalten
FHA---r2
// JOBNAME: "ETIKETT1"
FBE---rETIKETT1
// TYPE: Endlosetiketten
// HEIGHT: 20.00 mm
// GAPLENGTH: 2.00 mm
// COLUMNS: 1
// COLUMN DISTANCE: 100.00 mm
FCDA--r1-----
FCCL--r0002000-
FCCM--r00000---
FCCHA-r1-----
FCCHB-r999-----
// SPEED: 50 mm/s
FCAA--r050-----
// CONTRAST: 200%
FCAB--r200-----
// LABELCONTROL: 0
FCDE--r0-----
// RIBBONCONTROL: 1
// RIBBONSENS: 0
FCDB--r10-----
// MATERIAL: Typ 1
FCDNA-r0-----
FCDNB-r1-----
FCDNC-r0000----
// SCAN MODE: 0
// SCAN PORT: 0
// NO READ: 0
// FEED LABEL: 0
FCDM--r0000----
// MIRROR LABEL: Nein
FCDO--r0-----
// TEXT (1/100 mm)
AM[1]1407;6907;0;4;0;3;398;398;8
BM[1]Test
// SETLINENO: 1 lines
FBAA--r1
// SETCOPIES: 1
FBBA--r00050---
// PRINT
FBC---r-----
```

The server output, for example, looks as follows:



```

C:\temp>cvnservw -p9010
Testserv: waiting for connect
@MSstart-ETIKETT1-50⤴
@MSProgress-ETIKETT1-10⤴
@MSProgress-ETIKETT1-20⤴
@MSHold-ETIKETT1-27⤴
@MSContinue-ETIKETT1-27⤴
@MSProgress-ETIKETT1-30⤴
@MSError-ETIKETT1-31-35-Druckkopf offen⤴
@MSAck-ETIKETT1-31⤴
@MSHold-ETIKETT1-31⤴
@MSContinue-ETIKETT1-31⤴
@MSProgress-ETIKETT1-40⤴
@MSProgress-ETIKETT1-50⤴
@MSDone-ETIKETT1-50⤴
Testserv: waiting for connect

```

14 Font Examples

14.1 Bitmap Fonts (Not Proportional)

Font 01 (8 x 11) Verhältnis 3:3
 Font 02 (12 x 17) Verhältnis 3:3
 Font 03 (18 x 26) Verhältnis 2:2
 Font 04 (40 x 56) Verhältnis 1:1
 Font 05 (18 x 32 mit Unterlängen) Verhältnis 2:2
 Font 07 (12 x 22 mit Unterlängen) Verhältnis 2:2

14.2 Bitmap Fonts (Proportional)

Font 21 (10 proportional) Verhältnis 3:3
 Font 22 (18 proportional) Verhältnis 2:2
 Font 23 (26 proportional) Verhältnis 2:2
 Font 24 (56 proportional) Verhältnis 1:1
 Font 28 (40 proportional) Verhältnis 1:1
 Font 29 (8 proportional) Verhältnis 5:5

14.3 Vector Fonts

Absender (Baskerville) Das ist ein Musteretikett
 für die Darstellung der
 Gold, Petra (Swiss Light) Schriftarten (Monospace)

Name, Vorname (Helvetica Bold)
 Goldstraße 456 (Swiss Light)

Straße, Hausnummer (Helvetica Bold)

23456 Golddorf (Swiss Light)
 PLZ, Ort (Helvetica Bold)

Musterlieferung
Bitte bestätigen Sie
den Empfang. (Brush Script)

Empfänger (Baskerville)

Mustermann, Max (Helvetica Roman)
 Name, Vorname (Helvetica Bold)

Musterstraße 123 (Helvetica Roman)
 Straße, Hausnummer (Helvetica Bold)

45678 Musterstadt (Helvetica Roman)
 PLZ, Ort (Helvetica Bold)

15 Index

#

*FBAA, line number	55
*FBAA, number of lines.....	81
*FBBA, total items of print order	82
*FBBB, layouts still to print.....	82
*FBBC, already printed layouts.....	82
*FBC, start printing.....	83
*FBE, start printing (assign printjob identifier)	83
*FBF, initialisation of page handling	83
*FBG, selection of current page.....	83
*FBH, order of pages	83
*FBI, generation of page w/o print start	83
*FCAA, print speed	93
*FCAB, contrast	54
*FCADG, back speed (intermittent mode)	93
*FCADH, operating mode (intermittent mode).....	93
*FCADI, layouts/cycle	53
*FCADK, print position	57
*FCADL, print offset (intermittent mode).....	94
*FCADLA, print offset.....	68
*FCADLA, print offset (continuous mode).....	87
*FCADO, operating mode	57
*FCADUA, encoder resolution (continuous mode)	88
*FCADUB, material feed (continuous mode)	88
*FCADUC, material speed (continuous mode).....	88
*FCADUD, material speed (continuous mode).....	87
*FCCB, buzzer	60
*FCCE, x offset	68
*FCCE, X offset.....	53
*FCCHA, number of columns.....	54
*FCCHB, column width	55
*FCCJ, alignment.....	54
*FCCK, keyboard layout	60
*FCCL, layout length 1/100 mm.....	53
*FCCN, codepage	59
*FCCO, layout width 1/100 mm	53
*FCCP, external print parameters.....	58
*FCDB, transfer ribbon control.....	57
*FCDC, operating mode (continuous mode).....	87
*FCDI, display language	58
*FCDJ, ribbon save (intermittent mode)	94
*FCDK, field handling.....	58
*FCDN, rotate layout.....	55
*FCDNC, material	54
*FCDO, flip layout	55
*FCDQA, transfer ribbon length.....	70
*FCDRA, ribbon save mode (continuous mode).....	89
*FCDRB, synchronization (continuous mode)	89
*FCDRCA, printhead move down time (continuous mode)	89
*FCDRDA, ribbon motor power (continuous mode)	90
*FCDREA, brake power for acceleration/braking (continuous mode) 90	
*FCDREB, brake power during printing (continuous mode).....	90

*FCDRFA, feedback distance (continuous mode).....	89
*FCDRFB, feedback speed (continuous mode)	90
*FCDS, flip/rotate layout	56
*FCDU, user guiding	59
*FCDW, hotstart	60
*FCFF, interface parameters	62
*FCGC, SOH/ETB.....	62
*FCGD, data memory	63
*FCGEA, reaction unknown questions	63
*FCHA, paper counter printing system	72
*FCHB, paper counter printhead	72
*FCIA, date	72
*FCIB, time.....	72
*FCIG, automatic clock adjustment	73
*FCIH, beginning of summertime.....	74
*FCII, end of summertime	74
*FCIJ, time shifting.....	74
*FCKA, password.....	75
*FCKB, function group (password)	75
*FCKDA, password function menu	76
*FCKDB, password favorites menu	76
*FCKDC, password memory card.....	76
*FCKDD, password printing manually	76
*FCLA, IP address (network)	64
*FCLB, netmask (network).....	64
*FCLC, gateway address (network).....	64
*FCLD, transmission mode (network).....	65
*FCLE, DHCP support (network)	65
*FCLF, print module name (network).....	65
*FCLMB, MAC address (network)	65
*FCLNI, NTP server IP (network)	66
*FCLNS, NTP status (network).....	67
*FCLNZ, time zone (network)	67
*FCLZ, reset network device (network)	67
*FCMBC, printhead closed	69
*FCMBD, printhead open.....	69
*FCMBH, compressed air sensor	68
*FCMBI, cover sensor.....	68
*FCMC, printhead temperature.....	70
*FCMDC, IN signal level (continuous mode)	91
*FCMDC, IN signal level (intermittent mode).....	95
*FCMDD, OUT signal level (continuous mode)	91
*FCMDD, OUT signal level (intermittent mode).....	95
*FCMDE, I/O protocol port (intermittent mode).....	95
*FCMDF, software input (continuous mode).....	91
*FCMDF, software input (intermittent mode)	96
*FCMDG, software output (continuous mode).....	92
*FCMDG, software output (intermittent mode)	96
*FCMG, printhead resistance	71
*FCMH, reset error.....	81
*FCMHA, error ID/error text	81
*FCMKC, online/offline.....	69
*FCMKD, reprint action	69
*FCMKE, standard layout	61
*FCMLA, ribbon prior warning	70
*FCMLB, ribbon prior warning diameter	70
*FCMLC, ribbon diameter	71

- *FCMLDA, mode (ribbon prior warning) 71
- *FCMQ, status print 84
- *FCNRA, custom logo..... 71
- *FCSDC, debounce start signal (intermittent mode) 96
- *FCSDDD, start signal delay (continuous mode) 92
- *FCSDDD, start signal delay (intermittent mode)..... 96
- *FCSDFA, continuous print (continuous mode)..... 92
- *FCSDFA, continuous print (intermittent mode) 97
- *FCSDFC, layout change confirmation..... 61
- *FCSDFD, print after measuring..... 61
- *FCSDJ, output signal (continuous mode)..... 92
- *FCSDJ, output signal (intermittent mode) 97
- *FD, start/stop command 81
- *FE, feed 84
- *FEB, ribbon feed..... 84
- *FF, test print 84
- *FGA, cancel print order 84
- *FMA, save layout (cf card)..... 77
- *FMB, load file (cf card) 77
- *FMC, delete layout (cf card) 77
- *FMD, format (cf card) 77
- *FMG, table of contents(cf card)..... 77
- *FMH, memory space (cf card) 78
- *FMI, create directory (cf card) 78
- *FMJ, delete directory (cf card)..... 78
- *FMJA, delete directory path (cf card) 78
- *FMK, change directory (cf card) 78
- *FMKB, standard directory via I/O (cf card) 79
- *FML, transfer file (cf card) 79
- *FMM, enquiry if the file exists (cf card)..... 79
- *FMP, size of cf card..... 79
- *FMS, drive status (cf card) 80
- *FZ, emulation..... 85

A

- alignment, layout 54

B

- back speed (intermittent mode)..... 93
- brake power (continuous mode)
 - during printing 90
 - for acceleration/braking 90
- buzzer..... 60

C

- clock adjustment, automatical
 - beginning of summertime 74
 - end of summertime 74
 - time shifting..... 74
- codepage..... 59
- column
 - number, column printing 54
 - width, column printing 55
- compact flash card
 - change directory 78
 - create directory 78
 - delete directory 78
 - delete directory path 78

delete layout	77
drive status	80
enquiry if the file exists	79
format card.....	77
load file.....	77
readout free memory space.....	78
save label.....	77
size of cf card.....	79
standard directory via I/O.....	79
transfer file	79
compressed air sensor	68
configuration and status	
autostatus	100, 101
saving.....	99
status enquiry	99
status return information	99
continuous mode (parameter sets)	
I/O parameters.....	91, 92
machine parameters	87, 88
ribbon save	89
continuous print (continuous mode)	92
continuous print (intermittent mode).....	97
contrast.....	54
cover sensor.....	68
custom logo	71

D

data format	
explanation	12
field attributes	13
field name	14, 15, 16, 17, 18
field properties	13
general information	11
Data format	
Field selection.....	18
data memory	63
date/time	
automatic clock adjustment	74
automatical clock adjustment	73
date	72
time	72
datum point (text, bar code, graphic)	9
debounce start signal (intermittent mode).....	96
device settings	
buzzer	60
codepage	59
display language.....	58
external print parameters.....	58
field handling.....	58
hotstart	60
keyboard layout	60
layout change confirmation.....	61
operating mode.....	57
print after measuring.....	61
print position	57
standard layout	61
transfer ribbon control.....	57
user guiding	59
DHCP support, network.....	65
display language	58

E	
emulation	85
encoder resolution (continuous mode)	88
external print parameters	58
F	
feed.....	84
feedback distance (continous mode)	89
feedback speed (continuous mode)	90
field handling	58
font examples	
bitmap fonts (not proportional).....	107
bitmap fonts (proportional).....	107
vector fonts	107
format identifier, date/time	41, 42, 43
G	
gateway address, network.....	64
generation, selected page	83
graphic set	
general graphic format.....	35
PCX format	35, 36
H	
hotstart.....	60
I	
I/O parameters (continuous mode)	
continuous print	92
IN signal level	91
OUT signal level	91
output signal	92
software input	91
software output	92
start signal delay.....	92
I/O parameters (intermittent mode)	
continuous print	97
debounce start signal.....	96
I/O protocol port	95
IN signal level	95
OUT signal level	95
output signal	97
software input	96
software output	96
start signal delay.....	96
I/O protocol port (intermittent mode)	95
IN signal level (continuous mode)	91
IN signal level (intermittent mode).....	95
initialisation of page handling	83
interface	
parameters.....	62
SOH/ETB	62
intermittent mode (parameter sets)	
I/O parameters.....	95, 96, 97
machine parameters	93, 94
IP address network.....	64
K	
keyboard layout	60

L

layout	
flip layout.....	55
flip/rotate	56
rotate layout.....	55
layout change confirmation	61
layout length in 1/100 mm	53
layout parameters	
alignment	54
column width.....	55
contrast	54
flip layout.....	55
flip/rotate layout	56
layout length in 1/100 mm.....	53
layout width in 1/100 mm.....	53
layouts/cycle	53
material	54
number of columns	54
number of lines	55
rotate layout.....	55
x offset	53
layout width in 1/100 mm.....	53
line number.....	81
lines (number), column printing.....	55

M

MAC address.....	66
machine parameters (continuous mode)	
encoder resolution	88
material feed	88
material speed	87, 88
operating mode.....	87
print offset.....	87
machine parameters (intermittent mode)	
back speed	93
operating mode.....	93
print offset.....	94
print speed.....	93
ribbon save	94
mask set	
bar code Aztec Code	30
Bar code CODABLOCK F.....	27
bar code DataMatrix	25
bar code GS1 DataMatrix	26
bar code MAXICODE.....	24
bar code PDF417.....	23
bar code QR Code.....	29
bar code, GS1 DataBar (RSS)	28
bar code, ITF	22
bar code, one-dimensional	21
internal graphic	32
line	31
rectangle	31
text.....	19, 20
material feed/encoder turn (continuous mode)	88
material selection	54
material speed (continuous mode).....	87, 88
monitored printing.....	103, 104, 105, 106

N

netmask, network	64
network	
DHCP support.....	65
gateway address.....	64
IP address.....	64
MAC address	66
netmask	64
NTP server IP	66
NTP status	67
print module name	65
reset network device.....	67
time zone (hour offset).....	67
transmission mode.....	65
NTP server IP	66
NTP status.....	67

O

offset values	
print offset	68
x offset	68
online/offline	69
operating mode	57
operating mode (continuous mode)	87
operating mode (intermittent mode)	93
order (pages to print).....	83
OUT signal level (continuous mode)	91
OUT signal level (intermittent mode).....	95
output signal (continuous mode)	92
output signal (intermittent mode).....	97

P

paper counter	
printhead	72
printing system.....	72
parallel data transmission, connection plan	7
parameter sets	
compact flash card.....	77, 78, 79, 80
data memory	63
date/time	72, 73, 74
device settings	57, 58, 59, 60, 61
emulation	85
I/O parameters (continuous mode)	91, 92
I/O parameters (intermittent mode)	95, 96, 97
interface	62
interface protocol	62
layout parameters	53, 54, 55, 56
machine parameters (continuous mode)	87, 88
machine parameters (intermittent mode).....	93, 94
network	64, 65, 66
offset values.....	68
password	75, 76
password favorites menu.....	76
password function menu.....	76
password memory card	76
password printing manually	76
printing	81, 82, 83, 84
ribbon save (continuous mode)	89, 90
service functions	69, 70, 71

password	75, 76
print after measuring	61
print module name.....	65
print offset.....	68
print offset (continuous mode).....	87
print offset (intermittent mode)	94
print order, cancel.....	84
print position	57
print speed (intermittent mode)	93
printhead	
resistance	71
temperature	70
printhead closed.....	69
printhead move down time (continuous mode)	89
printhead open	69
printing	
cancel print orders	84
feed	84
generation of selected page	83
initialisation of page handling	83
item number of print order	82
number of lines	81
print order	83
reset error	81
ribbon feed.....	84
selection of current page	83
start printing	83
start/stop command	81
status printing	84
test print	84
printing, start.....	83

R

reaction, unknown questions.....	63
reprint action.....	69
reset error	81
reset network device	67
ribbon feed	84
ribbon save (continuous mode)	
brake power during printing	90
brake power for acceleration/braking	90
feedback distance.....	89
feedback speed	90
printhead move down time	89
ribbon motor power.....	90
ribbon save mode	89
synchronization.....	89
ribbon save (intermittent mode)	94
ribbon save mode (continuous mode).....	89
rotation (text, bar code, graphic)	9

S

sensors	
compressed air	68
cover	68
serial data transmission	
connection plan RS232.....	6
connector assignment.....	5

service functions

- custom logo 71
- online/offline..... 69
- printhead resistance 71
- printhead temperature 70
- reprint action 69
- transfer ribbon length..... 70
- transfer ribbon prior warning..... 70
- transfer ribbon prior warning, diameter..... 70
- transfer ribbon prior warning, mode..... 71
- software input (continuous mode) 91
- software input (intermittent mode)..... 96
- Software output (continuous mode) 92
- software output (intermittent mode) 96
- SOH/ETB..... 62
- standard layout..... 61
- start signal delay (continuous mode) 92
- start signal delay (intermittent mode) 96
- start/stop command..... 81
- status print..... 84
- synchronization (continuous mode) 89

T

- test print..... 84
- text set
 - example 34
 - general information 33
- time zone (hour offset) 67
- transfer ribbon control 57
- transfer ribbon length 70
- transfer ribbon motor power (continuous mode) 90
- transfer ribbon prior warning 70
 - diameter..... 70
 - mode..... 71
- transmission mode 65

U

- user guiding..... 59

V

variables

- check digit..... 50
- counter 38
- counter, extended..... 39
- currency variable 44
- date/time 40, 41, 42, 43
- EPC (electronic product code)..... 49
- GS1-128 Parser 48
- link field..... 37
- memory card data..... 48
- set structure 37
- shift variable..... 45
- substring 51
- user guiding 46
- user guiding with mask 47

X

- x offset..... 53, 68



Carl Valentin GmbH
Neckarstraße 78 – 86 u. 94 . 78056 Villingen-Schwenningen
Phone +49 7720 9712-0 . Fax +49 7720 9712-9901
info@carl-valentin.de . www.carl-valentin.de